



US008055269B2

(12) **United States Patent**
Feher

(10) **Patent No.:** **US 8,055,269 B2**
(45) **Date of Patent:** **Nov. 8, 2011**

(54) **TIME CONSTRAINED SIGNAL MIMO
WIRELESS AND WIRED COMMUNICATION
METHOD**

4,567,602 A 1/1986 Kato et al.
4,584,880 A 4/1986 Matzuk
4,644,565 A 2/1987 Seo et al.

(Continued)

(76) Inventor: **Kamilo Feher**, El Macero, CA (US)

FOREIGN PATENT DOCUMENTS

AU 2005335219 1/2010

(Continued)

(*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 0 days.

OTHER PUBLICATIONS

U.S. Appl. No. 09/370,360, filed Aug. 9, 1999, Feher, K.

(Continued)

(21) Appl. No.: **13/020,513**

(22) Filed: **Feb. 3, 2011**

(65) **Prior Publication Data**

US 2011/0150496 A1 Jun. 23, 2011

Related U.S. Application Data

(63) Continuation of application No. 12/753,802, filed on Apr. 2, 2010, now Pat. No. 7,885,650, which is a continuation of application No. 12/102,147, filed on Apr. 14, 2008, now Pat. No. 7,693,229, which is a continuation of application No. 11/023,254, filed on Dec. 28, 2004, now Pat. No. 7,359,449.

(51) **Int. Cl.**
H04W 72/00 (2009.01)
H04B 1/38 (2006.01)

(52) **U.S. Cl.** **455/454; 455/574**

(58) **Field of Classification Search** **455/454, 455/574**

See application file for complete search history.

(56) **References Cited**

U.S. PATENT DOCUMENTS

3,702,476 A 11/1972 Nathanson
3,944,926 A 3/1976 Feher
4,030,033 A 6/1977 Bibl et al.
4,229,821 A 10/1980 De Jager et al.
4,339,724 A 7/1982 Feher
4,350,879 A 9/1982 Feher
4,531,221 A 7/1985 Chung et al.


Primary Examiner — Lester Kincaid

Assistant Examiner — Joel Ajayi

(57) **ABSTRACT**

A method and system for receiving and processing in a wireless device a Radio Frequency Identification (RFID) device generated signal and a sensor generated signal. Receiving and processing a data signal into a processed ultra narrowband (UNB) and a processed ultra wideband (UWB) signal and providing processed UNB and UWB signal to a selector for selection of UNB or UWB signal and for providing selected UNB or UWB signal to a transmitter for transmission. A transmitter and receiver having a Multiple Input Multiple Output (MIMO) antenna system. Processing a signal into a Time Division Multiple Access (TDMA) and a Code Division Multiple Access (CDMA), Time Constrained Signal (TCS) waveform shaped and Long Response (LR) filtered signal. Receiving and processing a Fiber Optic Communication (FOC) network provided signal and processing a UNB processed signal into a processed spread spectrum signal. Processing and modulating a UNB signal into a missing cycle (MCY) processed modulated signal and into a phase reversal keying (PRK) modulated signal. Processing a signal into a clock shaped signal and processing and modulating a Radio Frequency Identification (RFID) processed signal into a processed UNB phase reversal keying (PRK) modulated signal and an infrared (IR) signal processor for receiving and processing an IR generated signal used in wireless device.

10 Claims, 22 Drawing Sheets



U.S. PATENT DOCUMENTS							
4,720,839	A	1/1988	Feher et al.	6,445,749	B2	9/2002	Feher
4,742,532	A	5/1988	Walker	6,448,022	B1	9/2002	Walker
4,745,628	A	5/1988	McDavid et al.	6,466,163	B2	10/2002	Naruse et al.
4,852,090	A	7/1989	Borth	6,470,055	B1	10/2002	Feher
4,945,549	A	7/1990	Simon et al.	6,522,895	B1	2/2003	Montalvo
4,962,510	A	10/1990	McDavid et al.	6,535,320	B1	3/2003	Burns
5,084,903	A	1/1992	McNamara et al.	6,535,561	B2	3/2003	Boesch et al.
5,103,459	A	4/1992	Gilhousen et al.	6,539,253	B2	3/2003	Thompson et al.
5,107,260	A	4/1992	Meissner	6,546,044	B1	4/2003	Dent et al.
5,157,686	A	10/1992	Omura et al.	6,574,211	B2	6/2003	Padovani et al.
5,185,765	A	2/1993	Walker	6,577,229	B1	6/2003	Bonneau et al.
5,282,222	A	1/1994	Fattouche et al.	6,591,084	B1	7/2003	Chuprun et al.
5,299,228	A	3/1994	Hall	6,665,348	B1	12/2003	Feher
5,313,173	A	5/1994	Lampe	6,711,440	B2	3/2004	Deal et al.
5,345,439	A	9/1994	Marston	6,745,126	B1	6/2004	Pavlak et al.
5,359,521	A	10/1994	Kyrtsos et al.	6,748,021	B1	6/2004	Daly
5,430,416	A	7/1995	Black et al.	6,748,022	B1	6/2004	Walker
5,479,448	A	12/1995	Seshadri	6,757,334	B1	6/2004	Feher
5,488,631	A	1/1996	Gold et al.	6,772,063	B2	8/2004	Ihara et al.
5,491,457	A	2/1996	Feher	6,775,254	B1	8/2004	Willenegger et al.
5,497,777	A	3/1996	Abdel-Malek et al.	6,775,371	B2	8/2004	Elsey et al.
5,535,432	A	7/1996	Dent	6,788,946	B2	9/2004	Winchell et al.
5,539,730	A	7/1996	Dent	6,807,564	B1	10/2004	Zellner et al.
5,550,881	A	8/1996	Sridhar et al.	6,823,181	B1	11/2004	Kohn et al.
5,564,076	A	10/1996	Auvrey	6,834,073	B1	12/2004	Miller et al.
5,572,516	A	11/1996	Miya et al.	6,842,617	B2	1/2005	Williams et al.
5,596,333	A	1/1997	Bruckert	6,865,395	B2	3/2005	Riley
5,608,722	A	3/1997	Miller	6,876,310	B2	4/2005	Dunstan
5,668,880	A	9/1997	Alajajian	6,876,859	B2	4/2005	Anderson et al.
5,745,480	A	4/1998	Behdash et al.	6,879,584	B2	4/2005	Thro et al.
5,757,858	A	5/1998	Black et al.	6,879,842	B2	4/2005	King et al.
5,778,024	A	7/1998	McDonough	6,889,135	B2	5/2005	Curatolo et al.
5,784,402	A	7/1998	Feher	6,897,952	B1	5/2005	Hagler
5,794,159	A	8/1998	Portin	6,901,112	B2	5/2005	McCorkle
5,815,525	A	9/1998	Smith et al.	6,906,996	B2	6/2005	Ballantyne
5,818,827	A	10/1998	Usui et al.	6,470,055	C1	8/2005	Feher
5,842,140	A	11/1998	Dent et al.	6,757,334	C1	8/2005	Feher
5,850,392	A	12/1998	Wang et al.	6,928,101	B2	8/2005	Feher
5,903,592	A	5/1999	Itaya	6,963,659	B2	11/2005	Tumey et al.
5,909,435	A	6/1999	Apelewicz	6,968,014	B1	11/2005	Bobier
5,909,460	A	6/1999	Dent	6,665,348	C1	1/2006	Feher
5,915,207	A	6/1999	Dao et al.	6,999,759	B2	2/2006	Harris et al.
5,930,303	A	7/1999	Walker	7,035,344	B2	4/2006	Feher
5,933,421	A	8/1999	Alamouti et al.	7,043,268	B2	5/2006	Yukie et al.
5,943,361	A	8/1999	Gilhousen et al.	7,057,512	B2	6/2006	Stilp
5,982,819	A	11/1999	Womack et al.	7,068,738	B2	6/2006	Lee et al.
5,999,519	A	12/1999	Basile et al.	7,079,584	B2	7/2006	Feher
6,006,105	A	12/1999	Rostoker et al.	7,103,085	B1	9/2006	Dabak et al.
6,008,703	A	12/1999	Perrott et al.	7,110,433	B2	9/2006	Feher
6,014,551	A	1/2000	Pesola et al.	7,133,456	B2	11/2006	Feher
6,035,212	A	3/2000	Rostoker	7,133,471	B2	11/2006	Feher
6,067,018	A	5/2000	Skelton et al.	7,162,236	B2	1/2007	Dorenbosch et al.
6,075,973	A	6/2000	Greeff et al.	7,228,136	B2	6/2007	Myllymaki
6,088,585	A	7/2000	Schmitt et al.	7,236,883	B2	6/2007	Garin et al.
6,101,174	A	8/2000	Langston	7,245,668	B2	7/2007	Feher
6,101,224	A	8/2000	Lindoff et al.	7,260,366	B2	8/2007	Lee et al.
6,107,959	A	8/2000	Levanon	7,260,369	B2	8/2007	Feher
6,128,330	A	10/2000	Schilling	7,263,133	B1	8/2007	Miao
6,167,099	A	12/2000	Rader et al.	7,280,810	B2	10/2007	Feher
6,177,861	B1	1/2001	MacLellan et al.	7,286,592	B2	10/2007	Pietila et al.
6,192,070	B1	2/2001	Poon et al.	7,319,878	B2	1/2008	Sheynblat et al.
6,195,563	B1	2/2001	Samuels	7,321,783	B2	1/2008	Kim
6,198,777	B1	3/2001	Feher	7,356,343	B2	4/2008	Feher
6,208,875	B1	3/2001	Damgaard et al.	7,359,449	B2	4/2008	Feher
6,216,012	B1	4/2001	Jensen	7,376,180	B2	5/2008	Feher
6,240,133	B1	5/2001	Sommer et al.	7,415,066	B2	8/2008	Feher
6,249,252	B1	6/2001	Dupray	7,418,028	B2	8/2008	Feher
6,256,508	B1	7/2001	Nakagawa et al.	7,421,004	B2	9/2008	Feher
6,269,246	B1	7/2001	Rao et al.	7,426,248	B2	9/2008	Feher
6,282,184	B1	8/2001	Lehman et al.	7,440,488	B2	10/2008	Feher
6,298,244	B1	10/2001	Boesch et al.	7,440,516	B2	10/2008	Kim et al.
6,321,090	B1	11/2001	Soliman	7,450,628	B2	11/2008	Feher
6,332,083	B1	12/2001	Shi et al.	7,457,385	B2	11/2008	Feher
6,389,055	B1	5/2002	August et al.	7,466,975	B2	12/2008	Feher
6,393,294	B1	5/2002	Perez-Breva et al.	7,483,492	B2	1/2009	Feher
6,418,324	B1	7/2002	Doviak et al.	7,545,883	B2	6/2009	Feher
6,424,867	B1	7/2002	Snell et al.	7,548,787	B2	6/2009	Feher
6,430,695	B1	8/2002	Bray et al.	7,555,054	B2	6/2009	Feher
				7,558,313	B2	7/2009	Feher

7,558,574 B2	7/2009	Feher	2008/0034409 A1	2/2008	O'Rourke et al.
7,561,881 B2	7/2009	Feher	2008/0043868 A1	2/2008	Feher
7,593,481 B2	9/2009	Feher	2008/0056399 A1	3/2008	Feher
7,593,733 B2	9/2009	Feher	2008/0057886 A1	3/2008	Feher
7,603,125 B2	10/2009	Feher	2008/0062856 A1	3/2008	Feher
7,627,320 B2	12/2009	Feher	2008/0120673 A1	5/2008	Dong et al.
7,630,717 B2	12/2009	Feher	2008/0161043 A1	7/2008	Feher
7,693,229 B2	4/2010	Feher	2008/0181151 A1	7/2008	Feher
7,711,368 B2	5/2010	Feher	2008/0188240 A1	8/2008	Feher
7,720,488 B2	5/2010	Feher	2008/0205535 A1	8/2008	Feher
7,725,114 B2	5/2010	Feher	2008/0212656 A1	9/2008	Feher
7,738,608 B2	6/2010	Feher	2008/0214164 A1	9/2008	Feher
7,769,386 B2	8/2010	Feher	2008/0219362 A1	9/2008	Feher
7,783,291 B2	8/2010	Feher	2008/0219385 A1	9/2008	Feher
7,787,882 B2	8/2010	Feher	2008/0240070 A1	10/2008	Feher
7,805,143 B2	9/2010	Feher	2008/0253275 A1	10/2008	Feher
7,809,374 B2	10/2010	Feher	2008/0253353 A1	10/2008	Feher
7,877,110 B2	1/2011	Feher	2008/0281585 A1	11/2008	Feher
2001/0016013 A1	8/2001	Feher	2009/0061852 A1	3/2009	Feher
2001/0020912 A1	9/2001	Naruse et al.	2009/0066667 A1	3/2009	Feher
2002/0001337 A1	1/2002	Chauncey et al.	2009/0076803 A1	3/2009	Feher
2002/0063622 A1	5/2002	Armstrong et al.	2009/0092114 A1	4/2009	Feher
2002/0085641 A1	7/2002	Baum	2009/0098852 A1	4/2009	Feher
2002/0086684 A1	7/2002	Pande et al.	2009/0181640 A1	7/2009	Jones
2002/0188575 A1	12/2002	Freemy, Jr.	2009/0240308 A1	9/2009	Feher
2002/0193108 A1	12/2002	Robinett	2009/0247187 A1	10/2009	Feher
2003/0063683 A1	4/2003	MacFarlane Shearer et al.	2009/0270113 A1	10/2009	Feher
2003/0120742 A1	6/2003	Ohgami et al.	2009/0310591 A1	12/2009	Feher
2003/0134464 A1	7/2003	Hidaka et al.	2010/0007711 A1	1/2010	Bell
2003/0147471 A1	8/2003	Simon et al.	2010/0029284 A1	2/2010	Feher
2003/0179833 A1	9/2003	Porco et al.	2010/0064025 A1	3/2010	Nelimarkka et al.
2004/0013166 A1	1/2004	Goodings	2010/0067595 A1	3/2010	Feher
2004/0017858 A1	1/2004	Rozenblit et al.	2010/0124920 A1	5/2010	Feher
2004/0081248 A1	4/2004	Parolari	2010/0208852 A1	8/2010	Feher
2004/0196923 A1	10/2004	Feher			
2004/0203377 A1	10/2004	Eaton et al.			
2004/0203715 A1	10/2004	Camp, Jr.			
2004/0208243 A1	10/2004	Feher			
2004/0249925 A1	12/2004	Jeon et al.			
2004/0253955 A1	12/2004	Love et al.			
2005/0068918 A1	3/2005	Mantravadi et al.			
2005/0090266 A1	4/2005	Sheynblat			
2005/0093584 A1	5/2005	Meacham			
2005/0094589 A1	5/2005	Camp, Jr.			
2005/0097595 A1	5/2005	Lipsanen et al.			
2005/0175116 A1	8/2005	Feher			
2005/0181810 A1	8/2005	Camp, Jr.			
2005/0185699 A1	8/2005	Feher			
2005/0185700 A1	8/2005	Pietila et al.			
2005/0202809 A1	9/2005	Lappetelainen et al.			
2005/0232135 A1	10/2005	Mukai et al.			
2005/0275549 A1	12/2005	Barclay et al.			
2005/0282588 A1	12/2005	Linjama et al.			
2006/0050625 A1	3/2006	Krasner			
2006/0057987 A1 *	3/2006	Nail et al. 455/168.1			
2006/0072646 A1	4/2006	Feher			
2006/0072647 A1	4/2006	Feher			
2006/0072684 A1	4/2006	Feher			
2006/0083320 A1	4/2006	Feher			
2006/0087432 A1	4/2006	Corbett			
2006/0088121 A1	4/2006	Feher			
2006/0135183 A1	6/2006	Zavada et al.			
2006/0146913 A1	7/2006	Feher			
2006/0274838 A1	12/2006	Feher			
2006/0293078 A1	12/2006	Qi et al.			
2007/0030116 A1	2/2007	Feher			
2007/0032220 A1	2/2007	Feher			
2007/0032246 A1	2/2007	Feher			
2007/0032250 A1	2/2007	Feher			
2007/0032266 A1	2/2007	Feher			
2007/0032832 A1	2/2007	Feher			
2007/0036203 A1	2/2007	Feher			
2007/0053471 A1	3/2007	Feher			
2007/0053472 A1	3/2007	Feher			
2007/0171874 A1	7/2007	Tanaka			
2007/0202890 A1	8/2007	Feher			
2007/0265018 A1	11/2007	Feher			
2008/0031126 A1	2/2008	Feher			
2008/0031310 A1	2/2008	Feher			

FOREIGN PATENT DOCUMENTS

CN	2005 8005 1233.3	1/2008
DE	212005000081.6	3/2008
JP	2005-020493	1/2005
JP	2005-086581	* 3/2005
JP	2008-523857	1/2008
KE	K 344	9/2009
KR	10-2008-7002382	1/2008
MX	MX/A/2008001123	1/2008
NZ	565452	1/2008
RU	2008107948	10/2005
SA	2008/00922	12/2008
SG	200800527-4	10/2005
WO	PCT/AU95/23485	* 8/1995
WO	PCT/IB97/00068	* 8/1997
WO	PCT/US98/16840	* 2/1999
WO	PCT/US99/17955	8/1999
WO	PCT/US99/17995	8/1999
WO	PCT/US2005/035931	10/2005
WO	PCT/US06/000486	* 7/2006

OTHER PUBLICATIONS

U.S. Appl. No. 09/370,361, filed Aug. 9, 1999, Feher, K.
U.S. Appl. No. 09/370,362, filed Aug. 9, 1999, Feher, K.
U.S. Appl. No. 09/385,693, Feher, K.
U.S. Appl. No. 60/095,943, filed Aug. 10, 1998, Feher, K.
U.S. Appl. No. 60/098,612, filed Aug. 31, 1998, Feher, K.
U.S. Appl. No. 60/615,678, filed Oct. 5, 2004, Feher, K.
U.S. Appl. No. 60/831,512, filed Jul. 18, 2006, Feher, K.
U.S. Appl. No. 11/927,686, filed Oct. 30, 2007, Feher, K.
U.S. Appl. No. 11/930,159, filed Oct. 31, 2007, Feher, K.
U.S. Appl. No. 11/937,467, filed Nov. 8, 2007, Feher, K.
U.S. Appl. No. 12/753,802, filed Apr. 2, 2010, Feher, K.
3GPP TS 25.213 V6.0.0 (Dec. 2003) 3rd Generation Partnership Project ; Technical Specification Group Radio Access Network Spreading and Modulation (FDD) (Release 6) 29 pages.*
3GPP TS 05.04 V8.4.0 (Nov. 2001) Technical Specification Group GSM/EDGE Radio Access Network; Digital cellular telecommunications system (Phase 2+); Modulation (Release1999); 3GPP:3rd Generation Partnership Project; (10 pages).*
Brown, C., Feher, K: "A reconfigurable modem for increased network capacity and video, voice, and data transmission over GSM

- PCS", IEEE Transactions on Circuits and Systems for Video Technology, pp. 215-224; vol. 6, No. 2, Apr. 1996 (10pages).*
- Brown, C.W.: "New Modulation and Digital Synchronization Techniques for Higher Capacity Mobile and Personal Communications Systems" Ph.D. Thesis University of California, Davis, Nov. 1996, pp. i-viii; 138-190; 269-272; 288-289;291.*
- Brown, C., Feher, K.: "A Flexible Modem Structure for Increased Network Capacity and Multimedia Transmission GSM PCS", Proceedings of the Fifteenth Annual Joint Conference of the IEEE Computer and Communication Societies (INFOCOM '96), 1996 (8 pages).*
- Furuscara, A. et al.: "EDGE: Enhanced Data Rates for GSM and TDMA/136 Evolution" IEEE Personal Communications, Jun. 1999, pp. 56-66.*
- Qualcomm: "MSM 6275 Chipset Solution", Qualcomm CDMA Technologies, San Diego, CA, 2004 (8 pages). Copyright 2004 Qualcomm.*
- Qualcomm: "MSM 6300 Chipset Solution", Qualcomm CDMA Technologies, San Diego, CA, 2004 (8 pages). Copyright 2004 Qualcomm.*
- Baisa, N.: "Designing wireless interfaces for patient monitoring equipment", RF Design Magazine Apr. 2005, www.rfdesign.com. (5 pages).
- Hickling, R.M.: "New technology facilitates true software-defined radio" RF Design Magazine Apr. 2005, www.rfdesign.com. (5 pages).
- Feher, K.: "Wireless Digital Communications: Modulation & Spread Spectrum Applications", Prentice Hall, Upper Saddle River, NJ 07458, Copyright 1995, Book ISBN No. 0-13-098617-8 (pages: front page; copyright page; pp. 164-177; 461-471; and 475-483).
- Holma, H., Toskala, A.: "WCDMA for UMTS Radio Access for Third Generation Mobile Communications", Second Edition, John Wiley & Sons Ltd. Chichester, West Sussex, England, Copyright 2002, ISBN 0-470-84467-1 (pages: front page; copyright page; pp. xv-xvi; 1-4; 90-95; 199-201; and 235-236).
- Tuttlebee, W.: "Software Defined Radio: Baseband Technology for 3G Handsets and Base Stations", John Wiley & Sons, Ltd., Chichester, West Sussex, England, Copyright 2004, ISBN 0-470-86770-1 (pages: front page; copyright page; pp. 1-3; 8-15; 34-39; and 274-279).
- Dobkin, D.M. and Wandinger, T.: "A Radio Oriented Introduction to Radio Frequency Identification"—RFID Tutorial, High Frequency Electronics, Jun. 2005, Copyright 2005 Summit Technical Media (6 pages).
- Dale Setlak: "Fingerprint sensors in Wireless handsets" a presentation at the OEM Design Expo Jun. 22, 2005, Wireless OEM Design Expo Online Conference & Exhibition, <http://www.reedbusinessinteractive.com/eom/index.asp> (38 pages).
- Kato, S. and Feher, K.: "XPSK: A new cross-correlated phase shift keying modulation technique", IEEE Trans. Commun., vol. COM-31, No. 5, May 1983, (pp. 701-707).
- Perrott et al.: "A 27-mW CMOS Fractional-N Synthesizer Using Digital Compensation for 2.5-Mb/s GFSK Modulation", IEEE Journal of Solid-State Circuits, Vol.32, No. 12, Dec. 1997, (pp. 2048-2060).
- Jian et al.: "An Efficient IF Architecture for Dual-Mode GSM/W-CDMA Receiver of a Software Radio," ... 1999 International Workshop on Mobile Multimedia Communications, IEEE, Nov. 15-17, 1999 San Diego, CA (pp. 21-24).
- Mangold et al.: "Software-definable Implementation of A Dual Mode TD-CDMA/DCS 1800 Transceiver Communication Summit, vol. 1, Jun. 1998, (5 pages).
- Morrison, I. S.: "ACE-8PSK: Band-Limited 8PSK With an Almost Constant Envelope", Tenth International Conference on Digital Satellite Communications, May 15-19, 1995, Brighton, UK. (pp. 325-331).
- Hyunchol Shin: "GSM RF Transmitter Design", Kewangwoon University, Seoul, Korea. Presented at PERC, ICU Aug. 19, 2004 (40 slides).
- Grieco, D.M. & Schilling, D.L.: "The Capacity of Broadband CDMA Overlaying A GSM Cellular System", IEEE Vehicular Technology Conference, Jun. 8-10, 1994, Stockholm, Sweden, 1994 IEEE (pp. 31-35).
- Malkemes et al.: "An Interoperable PACS and DCS1900 Subscriber Unit Radio Architecture", Sixth IEEE International Symposium, PIMRC'95: Personal Indoor and Mobile Radio Communication, Sep. 27-29, 1995, Toronto, Ont. Canada, 1995 IEEE (pp. 1149-1154).
- Bitkom: "RFID White Paper Technology, Systems, and Applications", Bitkom German Association for Information Technology, German Version published Aug. 2005, and English Version published Dec. 2005. The English Version published Dec. 2005 has been used in Applicant's search.
- Nokia: Nokia 5140i phone; Nokia 5140i NFC Shell User Guide "Issue 1.0, May 4, 2006; Nokia 6131 NFC User Guide in English" Issue 1, Feb. 6, 2007; Nokia Field Force Solution is an easy-to-use, flexible management tool especially designed to help enterprise improve their mobile and field-based business operations Copyright 2007.
- Quorum articles and publications downloaded from www.quorumsystems.com on Jun. 24, 2007, including: Why Convergence? The Sereno Platform. Sereno QS1000, QS 2000 and QS 3000, Copyright 2006 Quorum.
- Kellerer, W. et al. "A communication gateway for infrastructure-independent 4G wireless access", this paper appears in: Communications Magazine, IEEE Publication Date: Mar. 2002 vol. 40, Issue: 3 pp. 126-131.
- Spiegel, S.J. and Kovacs, I.G. "An efficient integration of GPS and WCDMA radio front-ends", IEEE Transactions on Microwave Theory and Techniques, vol. 52, Issue 4, Apr. 2004 pp. 1125-1131.
- Walker, H.R.: "Understanding Ultra Narrowband Modulation" from Microwaves and RF Dec. 1, 2003 downloaded from: <http://www.highbeam.com/doc/1P3-523237701.html>.

* cited by examiner




FIG. 1




FIG. 2




FIG. 3




FIG. 4

PRIOR ART




FIG. 5

PRIOR ART




FIG. 6




FIG. 7




FIG. 8




FIG. 9




FIG. 10




FIG. 11




FIG. 12




FIG. 13




FIG. 14







FIG. 15




a) NRZ 1001 non-balanced pattern



c) Missing Cycle MCY 1:8




b) NRZ1001 balanced pattern




d) Phase Reversal Keying (PRK) 1:8

FIG. 16





a) Missing Cycle 1:4



b) Phase Reversal 1:4 at start for Zero state only

FIG. 17



c) Single cycle per bit with one waveform for the 0 State and other waveform for the one state

FIG. 18




FIG.19




Fig.20




Fig.21




Fig. 22

TIME CONSTRAINED SIGNAL MIMO WIRELESS AND WIRED COMMUNICATION METHOD

RELATED APPLICATIONS

This application is filed as a continuation application of U.S. utility patent application Ser. No. 12/753,802 filed on Apr. 2, 2010, entitled: "Adaptive Coding and Modulation with MIMO", and U.S. utility patent application Ser. No. 12/102,147, filed on Apr. 14, 2008, entitled: "Transmission of Signals in Cellular Systems and in Mobile Networks", and of U.S. utility patent application Ser. No. 11/023,254, filed on Dec. 28, 2004 entitled: "Data Communication for Wired and Wireless Systems", now U.S. Pat. No. 7,359,449. In this continuation application, Applicant corrected certain typographical errors which were noticed by Applicant in the Ser. No. 11/023,254 and in the previously submitted applications.

This application claims the benefit under 35 U.S.C. 119(e) of U.S. Provisional Patent Application Ser. No. 60/615,678 entitled "ULTRA WIDEBAND, ULTRA NARROWBAND AND RECONFIGURABLE INTEROPERABLE SYSTEMS" filed on Oct. 5, 2004 by Applicant Feher, K., Ref. No. [21] and incorporated herein by reference.

The following three (3) related U.S. patent applications are co-pending: U.S. utility patent application Ser. No. 11/023,279, Ref. No. [21], Feher, K., submitted to the United States Patent and Trademark Office (USPTO) on Dec. 22, 2004 and filed by the USPTO on Dec. 28, 2004, entitled "BROADBAND, ULTRA WIDEBAND AND ULTRA NARROWBAND RECONFIGURABLE INTEROPERABLE SYSTEMS"

U.S. Utility patent application Ser. No. 11/102,896, Ref. No. [22], Feher, K., submitted to the United States Patent and Trademark Office (USPTO) on Dec. 22, 2004, entitled "HYBRID COMMUNICATION AND BROADCAST SYSTEMS"

U.S. Utility patent application Ser. No. 11/023,254, Ref. No. [23], Feher, K., submitted to the United States Patent and Trademark Office (USPTO) on Dec. 22, 2004 and filed by the USPTO on Dec. 28, 2004, entitled "DATA COMMUNICATION FOR WIRED AND WIRELESS COMMUNICATION"

FIELD OF THE INVENTION

This invention pertains generally to radio frequency (RF) spectrally efficient and power efficient systems, to ultra wideband (UWB), to wideband, to broadband, to spectral efficient, to narrowband, ultra narrowband (UNB) communication, to efficient communication and broadcasting systems, modulation and demodulation (Modem), architectures for baseband, intermediate frequency (IF) and radio frequency (RF) implementations. Bit stream processing, shaping of data signals and shaping or processing of clock and carrier waveforms leads to spectrally efficient and power efficient shaped radio-frequency (RF) waveforms and wavelets.

ACRONYMS

To facilitate comprehension of the current disclosure, some of the acronyms used in the prior art and/or in the current disclosure are highlighted in the following LIST of acronyms: 2G Second generation or 2nd generation
3G Third Generation or 3rd generation
AMC Adaptive Modulation and Coding
ACM Adaptive Coding and Modulation

BRA Bit Rate Agile
BWA Broadband Wireless Access
CDMA Code Division Multiple Access
CM Clock Modulated
CS Code Selectable
CSMA Collision Sense Multiple Access
CL Clock Shaped
EDGE Enhanced Digital GSM Evolution; Evolution of GSM or E-GSM
FA Frequency Agile (selectable or switched IF or RF frequency)
FOC Fiber Optic Communication
GPS Global Positioning System
IR Infrared
LR Long Response
MAW Modified Amplitude Wavelets
MAWM Modified Amplitude Wavelet Modulation
MCH Missing Chip
MCY Missing Cycle
MCYM Missing Cycle Modulation
MFS Modulation Format Selectable
MIMO Multiple Input Multiple Output
MMIMO Multimode Multiple Input Multiple Output
NRZ Non Return to Zero
PMK Phase Modification Keying
PPM Pulse Position Modulation
PRK Phase Reversal Keying
RFID Radio Frequency Identification
STCS Shaped Time Constrained Signal
TCS Time Constrained Signal
UMTS Universal Mobile Telecommunication System
UNB Ultra Narrow Band
UWB Ultrawideband
UWN Ultrawideband—Ultra Narrow Band
W waveform, wavelet or wave (signal element)
WCDMA Wideband Code Division Multiple Access

CITED REFERENCES—PARTIAL LIST OF RELEVANT LITERATURE

Several references, including issued United States patents, pending US patents, and other references are identified herein to assist the reader in understanding the context in which the invention is made, some of the distinctions of the inventive structures and methods over that which was known prior to the invention, and advantages of this new invention, the entire contents of which being incorporated herein by reference. This list is intended to be illustrative rather than exhaustive.

All publications including patents, pending patents, documents, published papers, articles and reports listed or mentioned in these publications and/or in this disclosure-patent/invention are herein incorporated by reference to the same extent as if each publication or report, or patent or pending patent and/or references listed in these publications, reports, patents or pending patents were specifically and individually indicated to be incorporated by reference.

CROSS REFERENCE TO U.S. PATENT DOCUMENTS

The following referenced documents contain subject matter related to that disclosed in the current disclosure:

Reference No.:

1. U.S. Pat. No. 6,748,022 Walker, H. R.: "Single Sideband Suppressed Carrier Digital Communications Method and System", Issued Jun. 8, 2004.

1. U.S. Pat. No. 6,445,737 Walker, H. R.: "Digital modulation device in a system and method of using the same", Issued Sep. 3, 2002.
2. U.S. Pat. No. 5,930,303 Walker, H. R.: "Digital Modulation Employing Single Sideband with Suppressed Carrier", Issued Jul. 27, 1999.
3. U.S. Pat. No. 5,185,765 Walker, H. R.: "High Speed Data Communication System Using Phase Shift Key Coding", Issued Feb. 9, 1993.
4. U.S. Pat. No. 4,742,532 Walker, H. R.: "High Speed Binary Data Communication System", Issued May 3, 1988.
5. U.S. Pat. No. 6,775,324 Mohan, C. et al.: "Digital Signal Modulation System", Issued Aug. 10, 2004.
6. U.S. Pat. No. 6,301,308 Rector, R.: "System and Method for High Speed Data Transmission", Issued Oct. 9, 2001.
7. U.S. Pat. No. 6,774,685 O'Toole et al.: "Radio Frequency Data Communication Device", Issued Aug. 10, 2004.
8. U.S. Pat. No. 6,774,841 Jandrell, L. H. M.: "Method and System for Processing Positioning Signals in a Geometric Mode", Issued Aug. 10, 2004.
9. U.S. Pat. No. 6,772,063 Ihara et al.: "Navigation Device, Digital Map Display System, Digital Map Displaying Method in Navigation Device, and Program", Issued Aug. 3, 2004.
10. U.S. Pat. No. 6,775,254 Willenegger et al.: "Method and Apparatus for Multiplexing High Speed Packet Data Transmission with Voice/Data Transmission", Issued Aug. 10, 2004.
11. U.S. Pat. No. 6,748,021 Daly, N.: "Cellular radio communications system," Issued Jun. 8, 2004.
12. U.S. Pat. No. 6,128,330 Schilling; D. L.: "Efficient shadow reduction antenna system for spread spectrum", issued Oct. 3, 2000.
13. U.S. Pat. No. 6,775,371 Elsey et al.: "Technique for Effectively Providing Concierge-Like Services in a Directory Assistance System", issued Aug. 10, 2004.
14. U.S. Pat. No. 6,735,238 McCorkle, J. W.: "Ultra wide-band communication system, method, and device with low noise pulse formation", issued May 11, 2004.
15. U.S. Pat. No. 6,198,777 Feher, K.: "Feher Keying (FK) Modulation and Transceivers Including Clock Shaping Processors", issued March 2001.
16. U.S. Pat. No. 6,470,055 Feher, K.: "Spectrally efficient FQPSK, FGMSK, and FQAM for enhanced performance CDMA, TDMA, GSM, OFDM, and other systems", issued Sep. 3, 2002.
17. U.S. Pat. No. 6,665,348 Feher, K.: "System and Method for Interoperable Multiple-Standard Modulation and Code Selectable Feher's GMSK, Enhanced GSM, CSMA, TDMA, OFDM, and other Third-Generation CDMA, WCDMA and B-CDMA", issued Dec. 16, 2003.
18. U.S. Pat. No. 6,757,334 Feher, K.: "Bit Rate Agile Third-Generation wireless CDMA, GSM, TDMA and OFDM System", issued Jun. 29, 2004.
19. U.S. Pat. No. 6,445,749 Feher, K.: "FMODE Transceivers Including Continuous and Burst Operated TDMA, FDMA, Spread Spectrum CDMA, WCDMA and CSMA," issued Sep. 3, 2002.

CROSS REFERENCE TO RELATED U.S. PATENT APPLICATIONS

Reference No. (continued):

20. U.S. pat Provisional Application Ser. No: 60/615,678, Applicant Feher, K. "ULTRA WIDEBAND, ULTRA NARROWBAND AND RECONFIGURABLE INTEROPERABLE SYSTEMS" filed on Oct. 5, 2004.
21. U.S. Utility patent application Ser. No. 11/023,279, Applicant Feher, K., submitted to the United States Patent and Trademark Office (USPTO) on Dec. 22, 2004 and entitled "BROADBAND, ULTRA WIDEBAND AND ULTRA NARROWBAND RECONFIGURABLE INTEROPERABLE SYSTEMS".
22. U.S. Utility patent application Ser. No. 11/102,896, Applicant Feher, K., submitted to the United States Patent and Trademark Office (USPTO) on Dec. 22, 2004 and entitled "HYBRID COMMUNICATION AND BROADCAST SYSTEMS".
23. U.S. Utility patent application Ser. No. 11/023,254, Feher, K., submitted to the United States Patent and Trademark Office (USPTO) on Dec. 22, 2004 and entitled "DATA COMMUNICATION FOR WIRED AND WIRELESS COMMUNICATION".
24. U.S. patent application Ser. No. 09/916054: Bobier, Joseph A.; (Cudjoe Key, Fla.); Khan, Nadeem; (Cudjoe Key, Fla.): "Suppressed cycle based carrier modulation using amplitude modulation" Pub. No.: US 2002/0058484, published May 16, 2002.
25. U.S. patent application Ser. No. 10/305109 McCorkle, John W. et al.; Pat. Pub. No 20030161411, published: Aug. 28, 2003.
26. U.S. patent application Ser. No. 10/360,346 Shattil, Steve J.; "Unified Multi-Carrier Framework for Multiple-Access Technologies," Pub. No.: US 2003/0147655, published Aug. 7, 2003.
27. U.S. patent application Ser. No. 10/205,478: K. Feher: "Spectrally Efficient FQPSK, FGMSK and FQAM for Enhanced Performance CDMA, TDMA, GSM, OFDM, and Other Systems," U.S. patent application Ser. No. 10/205,478, filed Jul. 24, 2002 Continuation of U.S. patent application Ser. No. 09/370,360 filed Aug. 9, 1999. Provisional Application No. 60/095,943 filed on Aug. 10, 1998.
28. U.S. patent application Ser. No. 10/831,562: K. Feher: "Adaptive Receivers for Bit Rate Agile (BRA) and Modulation Demodulation (Modem) Format Selectable (MFS) Signals". Filed on Apr. 23, 2004, Continuation of Ser. No. 09/370,362 filed Aug. 9, 1999.
29. U.S. patent application Ser. No. 10/831, K. Feher: "CDMA, W-CDMA, 3rd Generation Interoperable Modem Format Selectable (MFS) systems with GMSK modulated systems", filed on Apr. 24, 2004, Continuation of Ser. No. 09/370,362 filed Aug. 9, 1999.
30. U.S. patent application Ser. No. 09/732,953, Pub. No.: US 2001/0016013 Published Aug. 23, 2001 K. Feher: Changed title to: "ULTRA EFFICIENT MODULATION AND TRANSCEIVERS" in Supplemental Amendment—submitted to USPTO on Aug. 13, 2004, Filed Dec. 7, 2000. Continuation of application Ser. No. 09/385,693 filed on Aug. 30, 1999; Provisional Application No. 60/098,612, filed Aug. 31, 1998. Now U.S. Pat. No. 6,198,777 issued Mar. 6, 2001.

CROSS REFERENCE TO RELATED PUBLICATIONS

31. Lin, J. S., Feher, K.: "Ultra Spectrally Efficient Feher keying (FK) Developments" Proceedings of the European Telemetry Conference (ETC), ETC-2002, Garmisch-Partenkirchen, Germany, May 2002

32. Furuscar, A. et al.: "EDGE: Enhanced Data Rates for GSM and TDMA/136 Evolution" IEEE Personal Communications, June 1999, (an IEEE Magazine); pp: 56-66
33. Brown, C., Feher, K.: "A reconfigurable modem for increased network capacity and video, voice, and data transmission over GSM PCS", IEEE Transactions on Circuits and Systems for Video Technology, pp: 215-224; Volume: 6, No. 2, April 1996 (10 pages)
34. Brown, C. W.: "New Modulation and Digital Synchronization Techniques for Higher Capacity Mobile and Personal Communications Systems" Ph.D. Thesis University of California, Davis, Nov. 1, 1996 pp:i-vii; 138-190; 269-272; 288-289; 291.
35. Brown, C., Feher, K.: "A Flexible Modem Structure for Increased Network Capacity and Multimedia Transmission in GSM PCS", Proceedings of the Fifteenth Annual Joint Conference of the IEEE Computer and Communication Societies (INFOCOM '96), 1996 (8 pages)
36. 3GPP TS 25.213 V6.0.0 (2003-12) 3rd Generation Partnership Project; Technical Specification Group Radio Access Network Spreading and Modulation (FDD) (Release 6) 28 pages
37. 3GPP TS 05.04 V8.4.0 (2001-11) Technical Specification Group GSM/EDGE Radio Access Network; Digital cellular telecommunications system (Phase 2+); Modulation (Release 1999); 3GPP: 3rd Generation Partnership Project; (10 pages)

BRIEF DESCRIPTION OF THE FIGURES

FIG. 1 a prior art Time Constrained Signal (TCS) processor and Long Response (LR) filter or LR processor architecture, also designated herein as a "Feher '055 processor" is illustrated, Ref. [17], Feher's U.S. Pat. No. 6,470,055.

FIG. 2 a prior art implementation of a narrowband system, also designated herein as Ultra Narrow Band (UNB) system, and/or a "Feher '777 processor" is shown, Ref [16], Feher's U.S. Pat. No. 6,198,777

FIG. 3 a prior art "Walker '737 modulator", used for Pulse Position Modulation (PPM), Phase Reversal Keying (PRK) and Missing Cycle (MC) transmission is illustrated, Ref [1-2], Walker's U.S. Pat. No. 6,445,737

FIG. 4 a prior art "McCorkle '238 transmitter", for Ultra Wide Band (UWB) systems, Ref. No. [15], McCorkle's U.S. Pat. No. 6,735,238 is shown

FIG. 5 a prior art illustrative spectrum, designated herein as Ultra Narrow Band (UNB) Spectrum from Feher's U.S. Pat. No. 6,198,777, Ref. No. [16], is illustrated

FIG. 6 is an embodiment of the current disclosure of an Ultra Narrow Band (UNB), an Ultra Wideband (UWB) and an efficient architecture containing Modified Amplitude Wavelets (MAW), Missing Chip (MCH), Missing Cycle Modulation (MCYM), Modulation Format Selectable (MFS), Multiple Input Multiple Output (MIMO), Phase Reversal Keying (PRK), Long Response (LR) processed or filtered signals and shaped Time Constrained Signal waveforms (TCS)

FIG. 7 shows a serial transmitter implementation with optional selected shaped Time Constrained Signal waveforms (TCS) processors and Long Response (LR) processed or filtered signals

FIG. 8 is an Adaptive Modulation and Coding (AMC) also designated as Adaptive Coded Modulation (ACM) Diversity-Multiple Output spread-spectrum and/or non spread spectrum transmitter

FIG. 9 represents the receiver section of a Multiple Input Multiple Output (MIMO) transmission/reception system with inputs from wired or wireless systems

FIG. 10 is a multimode Multiple Input Multiple Output (MIMO) interoperable UWB, UNB and efficient transmitter system with 2nd generation (2G), 3rd generation (3G) and 4th generation (4G) cellular systems

FIG. 11 represents a parallel multimode and optional multiprocessor, multiple modulator reconfigurable transmitter architecture with Multiple Input Multiple Output (MIMO) capability

FIG. 12 shows receiver embodiments with and without crystal filters

FIG. 13 is a reconfigurable single or multiple and interoperable transmitter architecture for Adaptive Modulation and Coding (AMC) systems for wireless systems, for wired systems, and/or UNB and UWB systems

FIG. 14 represents an alternative receiver architecture

FIG. 15 is an embodiment of band-pass filters (BPF) with crystal filters and/or switched crystal filters.

FIG. 16 presents a 1st set of sample waveforms, including NRZ 1001 non-balanced and balanced data patterns, Missing Cycle Modulation 1:8 modulated signals and Phase Reversal Keying (PRK) with 8 cycles per bit

FIG. 17 illustrates a 2nd set of sample waveforms: a) Missing Cycle 1:4 modulation with 4 cycles per bit and b) Phase Reversal 1:4 modulation with phase reversals at start of bits for zero states

FIG. 18 illustrates a 3rd set of sample waveforms a) having 4 cycles per bit with reduced amplitudes for zero (0) states; b) Single cycle per bit with zero transmit value for zero signal states; c) Single cycle per bit with one waveform transmission for the 0 state and an other waveform for the one state

FIG. 19 is an embodiment of an ultra narrowband (UNB) processor and/or modulator connected to an ultra wideband (UWB) system and/or to a spread spectrum processor/transmitter; combinations and/or connections of UNB and of UWB systems lead to ultra wideband and ultra narrowband (UWN) systems

FIG. 20 shows block diagrams of cascaded (in-series) hybrid systems, including a cascaded GSM or EDGE, of cascaded Infrared (IR) or GSM or CDMA or TDMA or UMTS systems.

FIG. 21 shows a cascade of multiple transmitters connected to one or more receivers, including single or plurality of baseband or IF or RF signals for GSM, EDGE, TDMA, spread spectrum CSMA, CDMA signals for reconfigurable operations with infrared (IR), Radio Frequency identification (RFID), GPS and sensor systems.

FIG. 22 shows a "hybrid" wired system interconnected with a wireless system, including interoperable wired fiber optic communication (FOC) interface and wireless systems.

NEED FOR THIS INVENTION

This invention addresses the need for new more efficient embodiments and implementation architectures of reconfigurable, adaptable, interoperable multimode ultra wideband - ultra narrowband (UWN) systems as well as a class of broadband wireless, broadband wireless access (BWA) and other spectral and power efficient communication systems. The BWA systems, disclosed herein include new implementation architectures and new "hybrid" embodiments for WCDMA, WiMAX, Wi-Fi, IEEE 802.11 and other IEEE specified systems, Local Multipoint Distribution Systems, other point to point systems and Multipoint Distribution Services (MDS)

will need more efficient, reduced size interoperable Multi-mode Multiple Input Multiple Output (MMIMO) hybrid operation, disclosed herein.

A network which incorporates UWB and UNB or other combinations of communications and or broadcast systems, is designated here as a "hybrid" system or "hybrid" network.

While prior art UWB systems, and systems, systems known as IEEE 802 standardized systems, WI-FI and/or Bluetooth provide communications for short distances some of these systems are not efficient for longer range/longer distance applications.

While spectrally efficient, narrowband and Ultra Narrow Band (UNB) systems are suitable for short as well as longer distances there are no disclosed embodiments for cost efficient—simple reconfigurable, interoperable communication and broadcasting system architectures, baseband, intermediate frequency (IF) and radio frequency (RF) implementations for Bit Rate Agile (BRA) systems, Adaptive Modulation and Coding (AMC) in case of UWB and UNB systems and the connection of these systems into an operating network. Processing the data signals, clock signals, and/or carrier waveforms of UWB, of UNB and of a class of other systems leads to shaped radio-frequency (RF) waveforms and wavelets. With Multiple Input Multiple Output (MIMO) diversity and protection system configuration the performance and capacity of these "hybrid" UWB and UNB systems may be further enhanced. For such systems more efficient and simpler architectures and implementations are disclosed.

In prior art patents and in other published documents and articles the aforementioned sets of systems were invented, studied and investigated separately from each other and joint-hybrid efficient and seamless, adaptive Modulation Format Selectable (MFS) and Bit Rate Agile (BRA) operation and joint embodiments of systems which operate as Adaptive Modulation and Coding (AMC) in flexible agile UWB and UNB systems in conjunction with other wireless and wired (cable, telephone, fiber optics) systems such as 2nd generation wireless systems, such as GSM systems, CDMA systems 3rd generation cellular systems and 4th generation wireless and cellular systems, including broadband systems were not disclosed.

BACKGROUND OF THE INVENTION

One set of communications systems contains highly spectral efficient, narrowband, very narrowband and ultra narrowband (UNB) systems; an other set contains broadband, wideband and ultra wideband (UWB) systems. Combinations and variations of these two sets of systems are designated herein with the generic term/acronym: Ultra wideband—ultra narrowband (UWN) systems.

The most important objectives of wireless communications, broadcasting, telemetry, location based systems GPS (Global Positioning System), Radio Frequency Identification systems (RFID), internet browsing infrared and in general "radio" systems as well as "wired" systems include: power and bandwidth or spectrum efficiency combined with robust Bit Error Rate (BER) performance in a noisy and/or strong interference environment. These Radio Frequency (RF) system objectives are specified in numerous systems including wireless communications and cellular systems, satellite systems, mobile and telemetry systems, broadcasting systems, cable, fiber optics and practically all communication transmission systems. Here we are using the term "Radio Frequency" (RF) in its broadest sense, implying that we are dealing with a modulated signal. The RF could be, for example, as high as the frequency of infrared or fiber optic

transmitters; it could be in the GHz range, e.g., between 1 GHz and 300 GHz, or it could be in the MHz range, e.g. between about 1 MHz and 999 MHz or just in the kHz range, such as used in telephony modems. The term RF could apply to Base-Band (BB) signals, to Pulse Position Modulated (PPM) signals, to Quadrature Modulated (for short "QM" or "QMOD") and to FM or AM or hybrid modulated signals, to non-quadrature modulated signals, or to un-modulated Carrier Wave (CW) signals or waveforms.

The cited publications, patents, pending patents and other published documents, reference numbers [1-31], and the references within the aforementioned publications contain definitions and descriptions of many terms used in this new patent disclosure and for this reason these "prior art" terms and definitions will be only briefly, on a case by case basis highlighted.

While the majority of prior patents and publications disclose systems which have a spectral efficiency of less than about 10 b/s/Hz [such systems include GMSK, BPSK, QPSK, QAM (e.g. 16-QAM; 64 QAM), Pulse Width Modulation (PWM), Pulse Position Modulation (PPM) and Pulse Duration Modulation methods] there is prior art which discloses implementations which could attain considerably higher spectral efficiencies, i.e. more than 10 b/s/Hz.

H. R. Walker's patents, references [1-5] and Feher's patent Ref. [16] describe information signal transmission methods which could attain ultra high spectral efficiencies of more than 10 b/s/Hz, designated herein as ultra narrowband (UNB) or ultra spectral efficient systems.

While the aforementioned issued patents and publications describe material of a background nature, they do not describe or suggest the subject matter of the present patent.

Prior to the description of the current invention, a brief review and highlights of prior art, contained in the description of FIG. 1 to FIG. 5 is presented. Some of the embodiments of the current disclosure use the terminology and acronyms and/or related acronyms to the ones used in the prior art and may use as part of the current embodiments acronyms/elements taken from prior art.

FIG. 1 a prior art Time Constrained Signal (TCS) processor and Long Response (LR) filter/or LR processor architecture, also designated herein as a "Feher '055" processor is illustrated. This TCS signal processor or waveform or wavelet architecture processor-generator in combination with LR filtered and or LR processed circuits has been used for agile cascaded mismatched (ACM) systems in Feher's U.S. Pat. No. 6,470,055, Ref. No. [17]. In brief, the term "agile" includes the meanings: flexible or changeable or tunable or selectable. The terms "cascade" and "cascaded" include the meanings: flow, or in series, or in sequence or in conjunction with. In other words cascaded also means that something is arranged in a series or succession of stages; that is each stage derives from or acts upon the product of a preceding stage. The term mismatch has the same meaning as in Feher's U.S. Pat. No. 6,470,055, Ref. No. [17] and Feher's US patents Ref. No. [18-19]. The Feher '055 processor is a unit, suitable for implementation of one of the elements of Ultra Narrow Band (UNB), Ultra Wide Band (UWB), combinations of Ultra Wide Band—Ultra Narrow Band (UWN) systems and other communications and broadcasting systems for system implementations and/or for Adaptive Modulation and Coding (AMC) system embodiments disclosed in the current invention.

FIG. 2 a prior art implementation of a narrowband system, also designated herein as ultra narrowband (UNB) system, and/or a Feher '777 processor is shown.

This implementation from Feher's U.S. Pat. No. 6,198,777, Ref. No. [16] is also designated herein as a Feher '777 processor, Feher Keying (FK) Modulation and Demodulation (modem)—system. It is suitable for implementation of a part of ultra narrowband (UNB), ultra wideband (UWB) embodiment and combinations of ultra wideband-ultra narrow band (UWN) systems, also designated herein as "hybrid" systems or hybrid networks. The UWN and other hybrid systems, disclosed in the current invention are suitable for Adaptive Modulation and Coding (AMC).

FIG. 3 a prior art Walker '737 modulator, used for Pulse Position Modulation (PPM), Phase Reversal Keying (PRK) and Missing Cycle (MC) transmission is illustrated. The Walker '737 Modulator for transmission and reception of ultra narrowband (UNB) signals uses Pulse Position Modulator (PPM) for Phase Reversal Keying (PRK) and Missing Cycle (MC) Signal Transmission; this FIG. 3 is from Walker's U.S. Pat. No. 6,445,737, Ref. No. [1-2].

FIG. 4 a prior art Ultra Wide Band(UWB) implementation of McCorkle et al., U.S. Pat. No. 6,735,238, Ref. No. [15] is illustrated.

FIG. 5 prior art illustrative spectrum, designated herein as Ultra Narrow Band (UNB) Spectrum, generated by one of the Feher '777 processors, from Feher's U.S. Pat. No. 6,198,777, Ref. No. [16], is shown.

SUMMARY OF THE INVENTION

This invention discloses new, efficient embodiments and implementation architectures of reconfigurable, adaptable, interoperable broadband wireless, multimode ultra wideband-ultra narrowband (UWN) systems as well as a class of broadband and other spectral and power efficient communication systems.

A network which incorporates UWB and UNB or other combinations of communications systems is designated here as a "hybrid" system or "hybrid" network.

Processing the data signals, of clock signals, and/or carrier waveforms of UWB, of UNB and of a class of other systems leads to shaped radio-frequency (RF) waveforms and wavelets. Multiple Input Multiple Output (MIMO) diversity and protection system configuration the performance and capacity of these "hybrid" UWB and UNB systems may be further enhanced. For such systems more efficient and simpler architectures and implementations are disclosed.

Specific Objectives of this invention include:

A 1st objective of this invention is to disclose implementations and embodiments which shape waveforms, wavelets, symbols, Radio Frequency (RF) cycles of previously disclosed non-shaped signals by means of optional TCS and/or LR processors and filters. Such shaping improves the spectral characteristics and or other performance parameters the system and leads to, in several cases simpler implementation architectures.

A 2nd objective is to process and generate UNB and UWB signals which have Modulation Format Selectable (MFS) waveforms or wavelets and are suitable for hybrid operation, diversity and protection systems including a new generation of Adaptive Modulation and Coding (AMC), Multiple Input Multiple Output (MIMO) systems which are interoperable with existing wireless systems, such as cellular GSM, GPRS, EDGE and CDMA and W-CDMA systems as well as with other conventional and broadband wireless and telephony systems.

DETAILED DESCRIPTION OF THE INVENTION AND OF ITS EMBODIMENTS

Detailed disclosure of several implementation architectures and embodiments of the current application is contained in this section.

FIG. 6 is an embodiment of an Ultra Narrow Band (UNB) architecture, containing in part a processor or modulator, element 6.1. Element 6.1 represents a processor and/or a modulator such as a Missing Cycle (MCY) or Phase Reversal Keying (PRK) modulator (e. g. Walker '737 modulator) which provides by connector 6.2 to the input of Time Constrained Signal(TCS) processing and/or shaping unit 6.3 the processed and/or modulated signal.

One or more Data Input (Data In) and Clock Input (Clock In) signals are provided to or from processor unit 6.1. The flow of Data Input (Data In) and Clock Input (Clock In) signals, depending on the preferred arrangement and application, could be either from the data/clock source unit, also designated as customer interface, not shown in FIG. 6, or towards the customer interface unit.

Processor 6.1 processes the incoming data/clock signals and generates one or more Modified Amplitude Wavelets (MAW), Missing Chip (MCH), Missing Cycle (MCY), Pulse Position Modulation (PPM), Phase Reversal Keying (PRK) signals with optional Modulation Format Selectable (MFS) waveforms or wavelets. Prior art references including Walker's '737 modulators, Ref No. [1-2], Feher's '777 processor, Ref. No. [16], Mohan Ref. No. [6] and McCorkle et al Ref. No. [15] disclose exemplary embodiments for Processor 6.1. The processor 6.1 provides output signals (waveforms, wavelets, symbols, or cycles are alternative terms herein for the term "signal") on single or multiple lead(s) 6.2.

In case if element 6.1 is implemented by a Walker '737 modulator or is implemented by one of the Feher's '777 processors then on connection lead 6.2 there are shaped or not-shaped waveforms. Units 6.3, 6.4 and 6.5 provide additional optional signal shaping and processing functions.

In the current invention the 6.1 processed prior art signals, or other signals, are provided to additional optional signal processing elements shown in FIG. 6. Unit 6.3 shapes the waveform generated in 6.1 and connected on lead 6.2 to processor 6.3. Processor 6.3 is providing a waveform shaping operation in a Time Constrained Signal (TCS) waveform (or wavelet) shaping processor. The processed/shaped TCS waveform output of processor 6.3 is connected to element 6.4 which contains a digital processor and a Digital to Analog (D/A) converter. The 6.4 digital processor may include serial to parallel data conversion or contain digital interface circuitry for suitable D/A interface. The output of the D/A is connected to a Long Response (LR) filter or processor, element 6.5. Since the prior art contains material on D/A converters and also on TCS and LR filters/processors, e.g. Feher's '777 processor, Ref. No. [16] and Feher's '055 processor Ref. No. [17], it would be redundant to describe here embodiments of TCS processors and of LR processors/filters.

In other words, Unit 6.3 is a waveform(or wavelet or symbol) shaping element which provides shaped TCS signals to Unit 6.4 which contains a digital processor, or analog processor/filter and/or a Digital to Analog Converter (D/A). The output of Unit 6.4 is connected to Unit 6.5, which is a Long Response (LR) filter or processor (baseband or IF or RF). The output of Unit 6.5 is provided on single or multiple lead 6.6 to optional selector(switch or splitter) 6.6b and to element 6.7 for subsequent modulation and/or to element 6.8 which provides signal splitting or switching or combining. The outputs

of element 6.8 are provided to one or more output leads and to one or more antenna units 6.9 and/or 6.10.

The term lead and its alternate term connection lead is interchangeably used in this application. The terms lead and connection lead are interpreted in a broad sense, including: the terms lead and connection lead mean that a connection is provided or there is a connection, or the signal is connected to a device or one or more signals are provided to a transmission medium. The term transmission medium includes the following generic meanings: transmitter port, transmitter interface, amplifier, cable connection, optic interface, telephone line interface and telephone line, antenna, wire or wireless input port.

Processor 6.13 receives signals from input lead(s) 6.12 and provides control signals on lead(s) 6.14 to unit 6.8. The signal outputs of unit 6.8 are provided for Diversity Transmission and/or splitting to a main channel and protection channel whereby the transmitted signals are controlled or selected by a control signal on lead(s) 6.12 and processed by element 6.13. The control signal could be obtained from a feedback path from a receiver or generated in the transmitter.

Depending on the application, performance specification and hardware, software or firmware requirements all units 6.1 to 6.14 in the aforementioned description are optional. Operational systems are obtained by “mix and match” selection of some of the elements. For example the embodiment could be limited to connection of Elements 6.3, 6.4, 6.5, 6.7 and 6.9 or other combinations or selections of connected elements. Lead 6.6 connects the shaped and processed signal to a waveform/signal modulator. Modulator 6.7 includes one or more conventional prior art modulators, for example FM, GMSK, GFSK, AM, DSB-AM, DSB-TC-AM DSB-SC-AM, BPSK, PPM, PAM, PWM, or Quadrature modulator such as QAM, QPSK, QPRS, 8-PSK or other. Modulated output(s) of element 6.7 is(are) provided to a splitter and/or switch unit 6.8 which provides the signal to one output, two outputs or more than two outputs, illustrated by antennas no 6.9 and 6.10. The split or switched multiple outputs of element 6.8 provide Multiple inputs to antennas 6.9 and 6.10. The FIG. 6 embodiment represents a Multiple Input Multiple Output(MIMO) transmitter, a transmitter which could have between 1 and N (where N is an integer number) inputs and/or between 1 and M (where M is an integer number) outputs and instead of antennas interface units for wired systems may be used. Splitter and/or switch element 6.8 provides signal splitting or selection into one or more transmit branches, illustrated by antennas 6.9 and 6.10. Instead of multiple antennas and multiple branches in some applications a single antenna or single interface transmit unit is used. Antennas 6.9 and 6.10 may be replaced with interface connections to wired systems. Lead(s) 6.11 and 6.12 are control leads provided to elements 6.7 and 6.13 respectively. These control leads provide signals for 6.7 modulator control/selection and for selection of 6.13 processor parameters for signal switch selection and/or for signal splitting. The control signals may be obtained from the receiver—via an information line or are generated in the transmitter for adaptive multi-mode signal selections. In FIG. 7, as well in other figures, the arrows—illustrated with two parallel lines, indicate that there could be one or more than one signals in the signal path.

FIG. 7 illustrates a serial transmitter implementation of the current invention. Unit 7.1 contains one or more of the following elements: A carrier wavelet (or carrier waveform or carrier cycle) generator, and/or one or more RF agile and Bit Rate Adaptive or Bit Rate Agile (BRA) (also designated as tunable or selectable bit rate) Frequency Synthesizer. The output signal or output signals of unit 7.1 are connected by

lead 7.2 to a switch or selector 7.3. The selected signal is (in the upper position of selector switches 7.3 and 7.6) by-passing unit 7.5, designated as Time Constrained Signal (TCS) processor unit 7.5. In the lower position of switches 7.3 and 7.6 the signal on lead 7.2 is connected through TCS unit 7.5 to lead 7.7 and to switch 7.8. Depending on the position of switches 7.8, 7.11, 7.13, 7.16, 7.18, and 7.21 the signal path is by-passing element 7.10 (long response LR filter or processor), 7.15 processor, 7.19 filter if the aforementioned switches are in the upper positions and passing through the said elements if the switched are in the lower positions. Combinations of upper and lower optional switch positions and optional elements are implemented by this diagram. Leads 7.2, 7.7, 7.12, 7.17, 7.22 continuing into 7.23, 7.26, 7.28 and 7.29 provide the signals to the next step of the transmitter and/or connect the signals to the transmission system. Optional signal conditioner 7.25 and splitter or combiner or switch unit 7.27 provide the signal(s) to output lead/output interface units 7.28 and 7.29. Control signal(s) (CS) or Clock Selector Data Signals (CSDS) are provided on leads 7.24. Leads 7.24 are connected to one or more of the aforementioned units/elements, including generators, processors, filters, switches, splitters and or combiners.

FIG. 8 is an other transmitter implementation of the current invention. The shown embodiment is for Adaptive Modulation and Coding (AMC), also designated as Adaptive Coding and Modulation (ACM), with or without diversity or protection switching, multiple input multiple output (MIMO) spread spectrum and non spread spectrum systems.

Lead 8.1 signal connections (leads) provide and/or receive the input data and/or clock signals to/from the transmit interface unit 8.2. One or more than one, multiple input signals are present on lead 8.1 and received by the subsequent units and are processed for transmission as single signals or more than one, multiple output signals. The interface unit 8.2 provides signals to one or more of the following optional units. Processor 8.3, is processing the input data and/or clock signals. The processed signals are provided to adaptive encoder 8.4, scrambler and/or spreader 8.5, AMC modulator 8.6, filter 8.7, amplifier 8.8, selector or splitter 8.9 and depending on the position of selector or splitter unit 8.9 to one or more transmit antennas, units 8.10 and 8.11 or to an interface unit or amplifier unit 8.12 for cabled or wired systems transmission or infrared or other transmission. Encoder 8.4, includes channel coding devices and error control, error detection and/or error correction devices.

Scrambler and/or spreader unit 8.5, includes optional cryptography—for security devices and or spreading functions for spread spectrum systems such as CDMA, W-CDMA and or frequency hopped spread spectrum (FH-SS) systems or other Direct Spread-Spread Spectrum Systems (DS-SS) or Collision Sense Multiple Access (CSMA) systems.

FIG. 9 represents a receiver embodiment of the current invention; a section of a Multiple Input Multiple Output (MIMO) transmission and reception system with inputs from wireless and from other systems is shown. Receive antennas 9.1a and 9.1b receive the transmitted radio frequency (RF) signals, while interface unit 9.1c and connection lead 9.1c receive the signals from a transmitter. Unit 9.2 is a combiner or switch selector unit which combines or selects one or more of the received signals. The combined or selected signals are provided to multiplier 9.3 for down conversion to an intermediate frequency (IF), or direct down conversion to baseband frequencies. The down-converter (multiplier 9.3) receives a signal from frequency synthesizer or oscillator unit 9.5. The frequency of the frequency synthesizer or oscillator unit 9.5 may be in synchronism—locked to a modulated frequency of

the received signal or maybe free running (asynchronous). Unit 9.5 is a filter or signal processor; this unit could be implemented at an IF frequency or in baseband, with non-ideal delay and non-ideal group delay characteristics or with approximately constant group delay or approximately zero group delay. The approximately zero group delay or approximately zero delay refers to a single frequency or to a specific frequency band and/or range of frequencies. Unit 9.6 provides additional optional signal filtering or processing, demodulation, synchronization and data regeneration or data reconstruction. Unit 9.7 descrambler or de-spreader descrambles and or de-spreads the signal. Unit 9.8 is a de-encoder; it de-encodes the encoded signal. Unit 9.9 provides additional signal processing, or signal conditioning and provides the processed signals to the receiving interface unit 9.10 and to one or more signal or one or more clock leads 9.11.

FIG. 10 shows an alternate transmitter embodiment of Multimode Multiple Input Multiple Output (MMIMO) systems of the current invention. FIG. 10 includes embodiment of a multimode MIMO interoperable Ultra Wideband (UWB), Ultra Narrow Band (UNB) transmitter system with 2nd generation (2G), 3rd generation (3G) and 4th generation (4G) cellular and other wireless and non wireless systems. This implementation shows structures for a combination of adaptive and other selections of multi-mode, multi-format, multiple rate systems, operated in a single mode or multiple-mode, or hybrid modes. While the combinations and use of the elements in FIG. 10 are new, FIG. 10 contains elements from the prior art and in particular from Schilling's U.S. Pat. No. 6,128,330, designated, listed also as reference number [13]. In addition to the prior art referenced units, the new units include 10.1, 10.4, 10.5, 10.6 and 10.7 and the combinations of these elements and interactions among them which enable a new generation of broadband, UWB, UNB and 2G or 3G or even 4G systems to operate with new structures. One of the novelties and counter-intuitive inventions of this disclosure and benefits of this application are in the hybrid adaptable-reconfigurable and "mix and match" blocks of FIG. 10. An example is the use of one or multiple ultra narrow band (UNB) processed and/or modulated signals in a spread spectrum mode. In such a hybrid UNB and spread spectrum structure the UNB processor first generates an UNB signal and afterwards one or more of the ultra narrow band signals is spread to a much wider band spread spectrum system in a Multimode Multiple Input Multiple Output (MMIMO) system structure. With such an architecture a higher spreading factor and higher performance is attainable than with prior art spread spectrum systems. Some of the other original discoveries and inventions of this disclosure are in the fact that the combinations of the structures shown in FIG. 10 process and generate spread spectrum, e.g. CDMA signals from 2G systems such as GSM or other modulated signals and spread the GSM or TDMA signals in one or more spreaders in an optional MMIMO structure. The disclosed multi-mode operation leads to seamless connectivity among different systems, among systems operated at different bit rates, having different modulation formats and different coding rules. On leads 10.1 and 10.2 the single or multiple signals and clocks are provided to or from the data and clock processor, Unit 10.3. Unit 10.4 contains a broadband and/or an UWB processor; unit 10.5 an UNB processor; Unit 10.6 a 2G, 3G or 4G processor. The 2G processor contains a GSM processor generator and or GSM/GPRS combined with EDGE and/or other processors. The processor designated as 3G contains part of a Universal Mobile Telecommunication System (UMTS) processor. Unit 10.7a selects or combines the signals and provides them to one or more optional Forward Error Correction

Coder (FEC) or other error control coding or error detection encoder(s), Unit 10.8. The signal selection or signal combination of unit 10.7a is directed/controlled by one or more control signals provided on leads 10.7b. The said control signals are programmed, user selected or operator selected signals, or obtained from the corresponding receivers. The encoded signal is connected to interleaver 10.9 and a preamble generator or pre-amble processor. Unit 10.10 provides additional data. The optional de-multiplexer, Unit 10.11 provides de-multiplexed signals to spreaders 10.12, 10.13, 10.14 and 10.15. A chip sequence generator provides one or more chip sequences to the aforementioned spreaders. The spread signals are provided to antennas 10.17, 10.18, 10.19 and 10.20. One or more of the spread signals are selected for transmission.

The embodiments and structures of FIG. 10 provide a large combination of hybrid "mix and match" of multiple mode interoperable systems including interoperable broadband, spread spectrum or non-spread spectrum systems, UMTS, UWB, UNB and of other communications, telemetry, broadcasting, broadband wireless, location finder and Radio Frequency Identification (RFID) systems.

FIG. 11 is an embodiment of a parallel hybrid "mix and match" transmitter architecture for Multimode Multiple Input Multiple Output (MMIMO) and Multiple Input Multiple Output (MIMO) systems of the current invention. On leads 11.1 and 11.2 one or multiple data and/or clock signals are provided to or from Data/Clock Interface unit 11.3. The Data/Clock Interface unit 11.3 processes the data and or clock signals. Clock processing includes processing of the clock rate of the data signal to generate clock rates which are the same and or are different then the clock rate of the input data. The clock rate of the input data is designated as the Clock rate or Clock of the data "CLD" signal. Within unit 11.3 clock rates which are integer multiples, sub-integer multiples or fractions of the data rate are generated. These selectable bit rates are designated as Clock Rates or Clock of the Control Data "CLC" signals. The CLC rates are in some embodiments integer multiples, sub-integer multiples or fractions of the data rate clock CLD, while in other embodiments the CLC rates are "not related" to the CLD rate; here the term "not related" to refers to a CLC rate which is not derived from the CLD signal, that is, it is in a free running operation and or asynchronous with the CLD rate. In some exemplary embodiments the CLD rate equals the CLC rate, while in other embodiments the CLC rate is four (4) times, or eight (8) times or, one thousand (1000) times, or seven and one third (7 and 1/3) times higher than the CLD rate or it is a fraction of the CLD rate. The CLC and CLD signals are provided through Unit 11.4 the Adaptive Modulation and Coding (AMC) unit, as processed control signals to control the operation and signal selection of units 11.5, 11.6, 11.7, 11.8, 11.9 and 11.10. Unit 11.4 is an Adaptive Modulation and Coding (AMC) unit; this unit is also designated as Adaptive Coding and Modulation (ACM) unit. Unit 11.4 processes received signals from Unit 11.3 and provides them to the Adaptive RF frequency and wave generation unit 11.5 and to processor unit 11.7. The outputs of the AMC contain data signals, control signals, clock signals and other signals (e.g. overhead signals/bits, pre-amble signals, known also as preamble bits or preamble words, signal quality monitor signals bits or chips). Adaptive RF frequency and wave generation unit 11.5 provides RF frequency agile or flexible RF waveforms to leads 11.6. One or multiple leads 11.6 are connected to processor unit 11.7. Within unit 11.7 under the control of the AMC, unit 11.4 processed and/or generated signals and/or under the control of the CLD rate or CLC rate clocks, one or more than one (one

or multiple) signals are connected and/or processed and connected to leads 11.8. Selection or combinations of Leads 11.6 and 11.8 are controlled by the output signal or output signals of unit 11.4 the AMC processor. Element 11.7.1 represents a connection between the input and output of processor 11.7. Element 11.7.2 is a digital and or analog signal processor or filter or a hybrid processor and filter which provides signal processing, shaping or filtering functions. Element 11.7.3 is an attenuator or amplifier, or unit gain connector which changes (modifies) the amplitude of the incoming signal and provides an amplitude modified output. Element 11.7.4 is a signal inverter; Element 11.7.5 is a signal inverter and amplitude modification device; Element 11.7.6 is a signal conditioner and or filter. This signal conditioner and/or filter element includes optional phase shifters, time delays and or switch components. The switch component of element 11.7.6 connects or disconnects(disables) the signal path between the input and output ports of element 11.7.6. If in a particular time (e.g. during a specific bit duration or a fraction or multiple bit durations) the said switch component is in one of its positions designated as ON, then the signal is forwarded to the output port, while for the other position of the switch designated as OF, the signal between input and output of element 11.7.6 is not connected. The AMC, Unit 11.4 provided control signals select or combine one or more of the unit 11.7 processed signals, processed by one or more of the aforementioned elements of unit 11.7, and provides these processed signals, through the selected leads 11.8 for subsequent amplification in unit 11.9, antenna selection or splitting combining in selector or splitter unit 11.10. One or multiple antennas, illustrated by units 11.11 and 11.12 are used for signal transmission. In an illustrative embodiment of FIG. 11 the RF frequency generator, unit 11.5 provides an un-modulated carrier wave (CW) signal to processor unit 11.7. One or more control signals, generated in the AMC unit 11.4 select for one multiple RF cycles attenuator element 11.7.3, while for other RF cycles a unit 11.7.2 processed RF cycle is selected. In an other illustrative embodiment of this invention, for each data signal (data bit or data symbol) representing a one (1) state four (4) RF cycles are provided through element 11.7.1 and a selected lead 11.8 to the transmit amplifier 11.9, while for each data signal representing a zero (0) state four (4) attenuated waveforms, also designated as wavelets, or in this case RF cycles are provided through element 11.7.3 and a selected lead 11.8 to the transmit amplifier 11.9. An illustration of the resultant 4 cycles per bit waveforms with modified amplitude zero state signal is shown in FIG. 18 and in particular in FIG. 18a; we designate such signals as Modified Amplitude Wavelets (MAW) and the process as Modified Amplitude Wavelet Modulation (MAWM).

In an other embodiment of this invention, for each data signal (data bit or data symbol) representing a one (1) state one (1) RF cycle is provided through element 11.7.1 to the transmit amplifier 11.9, while for each data signal representing a zero (0) state one (1) RF cycle is disconnected, that is in element 11.7.6 it is not connected to transmit amplifier 11.9. This case is referred to as Missing Cycle Modulation (MCM); the MCM has Missing Cycles (MCY) and or Missing Chips (MCH), i.e. not transmitted cycles (disconnected cycles or disconnected fractions of cycles) in the transmitted signals. In FIG. 16 and in particular in FIG. 16c a Missing Cycle Modulated (MCM) signal pattern for a sample data pattern of 1001 bits is shown, with 1 missing cycle from 8 cycles for zero state signals and no missing cycles for 1 state signals. This modulation format is designated as missing cycle 1:8 modulation or MCY 1:8.

In an other embodiment of this invention, for each data signal (data bit or data symbol) representing a one (1) state eight (8) RF cycles are provided through element 11.7.1 to the transmit amplifier 11.9, while for each data signal representing a zero (0) state one out of eight RF cycles has its output phase inverted (relative to the input phase), or has its phase modified (relative to the input phase); these phase inversion or phase reversal and phase modification processes are implemented in element 11.7.5. These cases are designated as Phase Reversal Keying (PRK) and Phase Modification Keying (PMK) respectively. Illustrative examples of Phase Reversal Keying (PRK) modulated signals are shown in FIG. 16d for a PRK modulated output signal a 1001 input data pattern with 1 out of 8 cycles having reversed phase for state zero (0) inputs, while for state one (1) inputs there are no phase reversals. The signal shown in FIG. 16d is designated as a Phase Reversal Keying (PRK) signal with 1:8 reversals, or PRK 1:8.

One of the structures of this invention generates for one state data different waveforms than for zero state data, such as illustrated in FIG. 18c. The illustrated waveform for a one state information bit (or one state chip in case of spread spectrum signals) generates one single cycle of a carrier waveform while for a zero state information bit (or zero state chip in case of spread spectrum signals) generates one single cycle of a carrier waveform which has a different waveform shape than that for the one state. For example a one state bit could correspond to a single RF cycle having a sinusoidal shape while the zero state bit corresponds to a single RF cycle which corresponds to a reduced amplitude non sinusoidal shape (e.g. periodic square wave signal or a periodic multi-level signal such as generated by a D/A converter). Signals, such as illustrated in FIG. 18c are generated by alternative selection for one and zero states, in Unit 11.7, elements 11.7.2 and 11.7.6 or other combinations of elements.

FIG. 12, FIG. 14, and FIG. 15, show receiver embodiments with and without crystal filters for reception and/or demodulation of a large class of signals, including reception and demodulation of the transmit signals disclosed in this application. In FIG. 12 the signal is received on lead 12.1 and connected to the receiver interface Unit 12.2. Receive interface Unit 12.2 contains splitters, amplifiers and filters and optional RF down-converters. The output signal of unit 12.2 is connected to one or multiple signal selection switch or signal splitter units 12.3. The selected or split signal(s) is/are provided by connection 12.5 and or processor and/or carrier recovery to switch or combiner elements 12.4. Switch or splitter and/or combiner control unit 12.10, receives control signals on lead 12.9 and determines the operation, regarding signal splitting, selection (switching) and combining, of units 12.3 and 12.5. The output of 12.4 is connected to one or multiple filters or processors, unit 12.6. Unit 12.6 contains a combination of Band-Pass-Filters (BPF), with or without Crystal Filters and or other filters such as Low-Pass-Filters (LPF) or High Pass Filters (HPF) and processors, or any combination or iteration of some or all of the aforementioned components. The 12.6 unit processed signals are connected to one or multiple demodulators, contained in Unit 12.7. The single or multiple demodulated data signals and clock signals are provided on output lead(s) 12.8.

FIG. 13 shows a reconfigurable and interoperable transmitter architecture for hybrid, Adaptive Modulation and Coding systems for wireless systems, for wired systems, for broadband wireless and/or UWB and UWB systems. On lead 13.1 data and clock signals are transferred to or from interface unit 13.2. Unit 13.2 processes the data/clock signals and provides a modified and/or new set of data and/or clock signals to the

optional second interface unit 13.5 for further processing. Under the control of Unit 13.9, processor unit 13.6, generator 13.7 and data unit 13.8 connect their respective outputs to the 3rd optional interface unit. The signals at the outputs of units 13.6, 13.7 and 13.8 are processed or conditioned shaped signals, such as Modified Amplitude Wavelets (MAW) signals, Missing Cycle Modulation (MCM); Missing Chips (MCH) modulated signals or Phase Reversal Keying (PRK) and Phase Modification Keying (PMK) signals, or other narrowband or Ultra-narrowband (UNB) signals. Embodiment of FIG. 13 implements multiple combinations and hybrid implementations of hybrid ultra wideband (UWB) and ultra narrowband (UNB) signals, designated as Ultra wideband and ultra narrowband (UWN) systems or hybrid UWN systems. The output signals of unit 13.10 are converted into Ultra Wideband (UWB) modulated signals by an UWB converter containing logic device 13.13, delay element 13.14, multipliers 13.15 and 13.18 and further processed by one or multiple amplifiers 13.19, and provided by connection 13.20 to transmit antenna 13.21. Transmit antenna 13.21 comprises one or multiple antennas. Multipliers 13.15 and 13.18 are connected to one or more of the short duration pulses illustrated by 13.16 and 13.17. These short duration pulses are generated in the control unit 13.9 or are obtained from other parts of the system.

FIG. 14 represents an alternative receiver architecture and embodiment for reception and/or demodulation of a large class of signals, including reception and demodulation of the transmit signals disclosed in this application. In FIG. 14 the signal is received by one or multiple antennas, shown as unit 14.1 and connected to one or more receiver amplifiers, designated as a Low Noise Amplifier (LNA) Unit 14.2. Receive amplifier provides the amplified signal to Band Pass Filter (BPF1), Unit 14.3. The subsequent multiplier (also known as mixer), unit 14.4, receives on one of its input ports the filtered signal and on its second input port it receives a signal from oscillator (OSC) or frequency synthesizer (FS) unit 14.6. Signal lead 14.5 may provide one or multiple control signals to unit 14.6. The multiplier output signal is filtered by a BPF or other type of filter of unit 14.7. The filtered signal is provided to an Automatic Gain Control (AGC) unit 14.8, which could have a control signal input on lead 14.9. The AGC output is provided to a nonlinear device or hard limiter, shown as unit 14.10 and to a splitter 14.11. In the upper branch of the split signal there is an amplifier 14.12 and a delay element 14.13, while in the lower branch there is a Carrier Recovery (CR) or other discrete signal recovery circuit, shown as unit 14.14 and an optional delay element 14.15. Subsequent mixer 14.16 receives the upper branch and lower branch processed signals and provides a mixed (down-converted) signal to unit 14.8, which has LPF or BPF or other signal processing elements. The single or multiple outputs are provided on lead 14.19.

In an alternative embodiment of FIG. 14 splitter element 14.11 and 14.14 carrier recovery and delay 14.15 are not required. Instead of these components oscillator or frequency synthesizer 14.17 provides inputs to the second port of multiplier (mixer) 14.16.

FIG. 15 is an embodiment of band-pass filters (BPF) with crystal filters and/or optional switched crystal filters. Receiver and/or demodulators include in several embodiments

BPF implementations. Part or all of band pass filtering (BPF) can be achieved by crystal filters. In some cases the crystal filters are between the signal path and ground while in others they are in a serial mode, that is in series with the signal path. On input lead 15.1 to the crystal filter the signal is

connected to a crystal filter 15.2 and to a high impedance device such as a FET amplifier, unit 15.4. The crystal contains an inductor "L" element, shown as element 15.3. In an alternate embodiment of the BPF the signal is received on lead 15.5 and connected to switch elements 15.6, 15.7, crystal 15.8 and high input impedance circuit 15.10. Block arrow 15.9 represents the control signals which turn on and off switch components 15.6 and 15.7. The control signals are obtained from the data source and the data pattern.

FIG. 16 illustrates sample waveforms of illustrative data patterns of NRZ baseband signals for a 1001 bit pattern. Both unbalanced NRZ patterns and NRZ patterns are shown. In the unbalanced case of the unbalanced NRZ patterns, FIG. 16a, the signal has +2 A amplitude for a one state and a zero (0) amplitude for a zero state. In the balanced case FIG. 16b the signal has a normalized +1 value for a one state and a normalized -1 value for a zero state. In FIG. 16c a Missing Cycle Modulated (MCM) signal pattern for a sample data pattern of 1001 bits is shown, with 1 missing cycle from 8 cycles for zero state signals and no missing cycles for 1 state signals. This signal is also designated as an MCY 1:8 signal. This modulation format is designated as missing cycle modulation (MCM) with 1:8 ratio. FIG. 16d shows a Phase Reversal Keying (PRK) modulated signal with a ratio of 1:8. The signal shown in FIG. 16d is designated as a Phase Reversal Keying (PRK) signal with 1:8 reversals, or ratio. It is also designated as of 1:8 reversals or PRK 1:8.

FIG. 17 represents a 2nd set of generated sample waveforms. In FIG. 17a missing cycle modulated waveform with a 1:4 ratio is shown, while in FIG. 17b a carrier phase reversal keying (PRK) modulated signal with a 1:4 phase reversal to non reversal ratio for zero state signals is shown; in these cases 4 cycles per bit, or alternatively for spread spectrum systems, 4 cycles per chip are illustrated.

FIG. 18 shows modulated signal/carrier waveforms for: (a) 4 cycles per bit with reduced amplitudes for zero states; (b) single cycle per bit with zero transmit state for zero state (zero logic state) signals; (c) Single cycle per bit with one waveform transmission for 0 state signals and an other waveform for one state signals.

FIG. 19 is an alternative "hybrid" embodiment of an ultra narrowband (UNB) processor and/or modulator connected to a broadband and/or an ultra wideband (UWB) system and/or to a spread spectrum processor/transmitter. Combinations, variations and/or connections of UNB and of UWB systems lead to hybrid ultra wideband and ultra narrowband (UWN) systems. Combinations of UNB of UWB and of spread spectrum systems are also designated as "hybrid" systems. Data input lead 19.1 provides binary data bits or other digital information to ultra narrowband (UNB) processor 19.3. Clock information into (In) the UNB processor and out of the UNB processor is provided on leads 19.2. The UNB processor provides UNB processed and/or UNB modulated signals to lead 19.4 for connection to splitter or switch element 19.5. The outputs of 19.5 are provided for further processing to the ultra wideband (UWB) unit 19.6 and/or to the spread spectrum unit 19.7, or to only one of these units. The UWB and spread spectrum signals are provided on leads 19.8 and 19.9 to the transmission medium. The signal flow-connection sequence between elements of FIG. 19 is interchanged in some of the alternative embodiments. For example the data and clock leads are provided to/and from the ultra wideband unit 19.6 and/or spread spectrum unit 19.7 and in such case the ultra wideband signal is provided to the ultra narrowband processor 19.3 and/or the output of the spread spectrum unit 19.7 is provided to the input of the ultra narrowband unit 19.3.

Variations and combinations of spread spectrum processors with ultra wideband or broadband processors and ultra narrowband processors lead to a new set of hybrid systems. Such hybrid systems are contrary to conventional communication systems and prior art technologies. While prior art systems disclose certain elements of this new set of hybrid systems, such as the embodiments of ultra narrowband systems, embodiments of ultra wideband systems and embodiments of spread spectrum systems, the prior art does not teach and it does not anticipate the use of these systems in a hybrid or combined mode as described in the current disclosure.

Unit 19.7 contains one or multiple prior art spread spectrum processors and/or one or more prior art spread spectrum modulators. Prior art spread spectrum processors and modulators include Direct Sequence Spread Spectrum (DSSS), Code Division Multiple Access (CDMA), Frequency Hopped Spread Spectrum (FHSS) and combinations, variations of other spread spectrum systems.

FIG. 20 shows embodiment of cascaded (in-series) hybrid systems, including a cascaded GSM or EDGE or other systems signal, generated or processed in unit 20.1 connected to one or multiple spread spectrum systems, unit 20.2, and a cascaded Infrared (IR) or GSM or CDMA or TDMA system, unit 20.3 cascaded (connected in series) with UMTS components or with other spread spectrum or other wired or wireless systems components.

FIG. 21 shows a cascade of multiple transmitters connected to one or more receivers. Unit 21.1, transmitter 1 is connected in baseband or IF or RF to Unit 21.2 transmitter 2. Either unit 21.1 or 21.2 contain one or a plurality of transmitters. Unit 21.3 contains one or more receivers. Single or plurality of baseband or IF or RF Signals, including GSM, EDGE, TDMA, spread spectrum CSMA, CDMA signals generated or processed in transmitter 1, unit 21.2, are connected for further processing in transmitter 2, unit 21.2. The cascaded processed signals are received by one or more receivers contained in unit 21.3. These receivers are in some embodiments parallel multiple path receivers, i.e. multiple receiver implementations) while in other embodiments are reconfigurable single path receivers. Unit 21.4 generates an infrared (IR) signal. Unit 21.5 is a signal processor and/or generator for Radio Frequency Identification (RFID) systems. Unit 21.6 is a GPS transmitter or receiver or entire GPS transceiver. Unit 21.7 is a sensor and processor device. One or more of the output signals of Units 21.4, 21.5, 21.6 and/or 21.7 are provided to processor Unit 21.8 for signal processing and or modulation. The Unit 21.8 processed signals are provided to Unit 21.9 for cellular or other land mobile or satellite system operation. The connection between the aforementioned optional blocks are at baseband or IF or RF.

FIG. 22 shows a "hybrid" wired system interconnected with a wireless system. Unit 22.1 contains a wired network unit, which includes one or more of telephone interface, fiber optic communication (FOC) interface or other wired interface units. The outputs or inputs of unit 22.1 provide or receive signals to or from wireless system 22.2. Wireless unit 22.2 contains one or more interface units or components of a wireless infrastructure or handset unit, such as a cellular base station, wireless base station, wireless terminal or handheld or other portable cellular or other wireless unit.

Having now described numerous embodiments of the inventive structure and method in connection with particular figures or groups of figures, and having set forth some of the advantages provided by the inventive structure and method, it should be noted that the embodiments described heretofore, as well as those highlighted below include optional elements or features that are not essential to the operation of the inven-

tion. The invention further provides methods and procedures performed by the structures, devices, apparatus, and systems described herein before, as well as other embodiments incorporating combinations and sub combinations of the structures highlighted above and described herein. The invention now being fully described, it will be apparent to one of ordinary skill in the art that many changes and modifications can be made thereto without departing from the spirit or scope of the appended claims.

I claim:

1. A method for more efficient architecture embodiment of power and spectral efficient, reconfigurable, hybrid, multimode receivers and processors of Radio Frequency Identification (RFID), sensor and Global Positioning System (GPS) signals and transmitters of ultra narrow band (UNB) and ultra wide band (UWB) wireless signals comprising steps of:

receiving and processing in a receiver and a processor of a wireless device, a RFID device generated signal into said processor processed RFID signal and a sensor generated signal into said processor processed sensor generated signal, wherein said sensor is in said wireless device;

receiving and processing in said wireless device a GPS generated signal into a GPS processed signal;

processing in said processor said processed RFID signal with said processed sensor signal and with said processed GPS signal into a processed UNB and a processed UWB signal; and

receiving and processing said processed UNB and said processed UWB signal and connecting said processed UNB and said processed UWB signal to a selector for selecting of said processed UNB or said processed UWB signal and for providing said selector selected UNB or said selector selected UWB signal to a transmitter for transmission, wherein said receiver and transmitter comprises a Multiple Input Multiple Output (MIMO) antenna system.

2. A system for more efficient embodiment of receiver and transmitter architectures of power and spectral efficient, reconfigurable, multimode ultra wide band (UWB) and Time Division Multiple Access (TDMA) wireless receiver and transmission devices comprising:

a receiver and a first processor for receiving and processing a first received UWB modulated data signal into a first UWB processed signal, and for providing said first UWB processed signal to an interface unit of a wireless device, for use by a user of said wireless device;

said first processor for receiving from said receiver a second received TDMA modulated data signal and for processing said second received TDMA modulated signal into a second TDMA processed signal, and for providing said second TDMA processed signal to said interface unit for use by said user of said wireless device;

a second processor for receiving, processing and providing to a transmit selector a third baseband data signal in said wireless device, into a second UWB processed signal, wherein said first and said second processed UWB signals and said first, second and third data signals are distinct signals;

said second processor for receiving, processing and providing to said transmit selector said third baseband data signal in said wireless device into a second processed TDMA signal, wherein said first and said second processed TDMA signals are distinct signals and said second processed TDMA signal comprises a processed Time Constrained Signal (TCS) waveform shaped and Long Response (LR) filtered signal; and

21

said transmit selector for receiving, selecting and providing said second processed UWB or said second processed TDMA signal to a transmitter for transmission of said selected signal, wherein said receiver and said transmitter comprises a Multiple Input Multiple Output (MIMO) antenna system.

3. A system for more efficient embodiment of receiver and transmitter architectures of power and spectral efficient, reconfigurable, multimode ultra wideband band (UWB) and Code Division Multiple Access (CDMA) wireless receiver and transmission devices comprising:

a receiver and a first processor for receiving and processing a first received UWB modulated signal into a first UWB processed signal and for providing said first UWB processed signal to an interface unit of a wireless device for use by a user of said wireless device;

said first processor for receiving from said receiver a second received CDMA modulated signal and for processing said second received signal into a first CDMA processed signal and for providing said first CDMA processed signal to said interface unit for use by said user of said wireless device;

a second processor for receiving, processing and providing to a transmit selector a first data signal in said wireless device into a second UWB processed signal, wherein said first and said second processed UWB signals are distinct signals;

said second processor for receiving, processing and providing to said transmit selector a second data signal in said wireless device into a second processed CDMA signal, wherein said first and said second processed CDMA signals are distinct signals and said second processed CDMA signal comprises a processed Time Constrained Signal (TCS) waveform shaped and Long Response (LR) filtered signal; and

said transmit selector for selecting said second processed UWB or said second processed CDMA signal and for providing said selected signal to a transmitter for transmission of said selected signal, wherein said receiver and said transmitter comprises a Multiple Input Multiple Output (MIMO) antenna system.

4. The method of claim 1, further comprising steps of processing an infrared (IR) signal and providing said processed IR signal to said interface unit of said wireless device wherein said processed UWB and said processed UNB signal comprises a clock shaped processed UWB and UNB signal and said processed UNB signal comprises a Time Constrained Signal (TCS) waveform shaped and Long Response (LR) filtered signal and further comprising steps of receiving and processing a Fiber Optic Communication (FOC) network provided signal and further comprising steps of processing said UNB processed signal into a processed spread spectrum signal.

5. The method of claim 1, further comprising steps of processing and modulating said processed UNB signal into a missing cycle (MCY) processed modulated signal, wherein said MCY processed signal is a clock shaped signal and processing and modulating said processed UNB signal into a phase reversal keying (PRK) modulated signal.

6. The system of claim 2, wherein said system further comprises a processor, a modulator and transmitter for generation of two distinct Ultra-Wideband (UWB) signals and of

22

two distinct Ultra-Narrowband (UNB) signals, wherein said UNB signal is a missing cycle (MCY) Clock Shaped (CS) signal and one of said processed UWB signal comprises a Time Constrained Signal (TCS) waveform shaped and Long Response (LR) filtered signal and further comprising a receiver for receiving and processing in said wireless device a Global Positioning System (GPS) generated signal into a GPS processed signal and for providing said GPS processed signal to said interface unit of said wireless device for use by said user of said wireless device.

7. The system of claim 2, further comprising a processor and modulator for processing a third data signal into a missing cycle (MCY) processed and modulated signal, wherein said MCY processed signal is a clock shaped signal and processing and modulating said data signal into a processed Ultra Narrowband (UNB) phase reversal keying (PRK) modulated signal.

8. The system of claim 2, further comprising a processor and modulator for processing a data signal into a missing cycle (MCY) processed and modulated signal, wherein said MCY processed signal is a clock shaped signal and processing and modulating a data signal into a processed UNB phase reversal keying (PRK) modulated signal and further comprising an infrared (IR) signal processor for receiving and processing an IR generated signal and further comprising a receiver for receiving and processing in said wireless device a Global Positioning System (GPS) generated signal into a GPS processed signal and for providing said GPS processed signal to said interface unit of said wireless device for use by said user of said wireless device.

9. The system of claim 3, wherein said system further comprises a processor, a modulator and transmitter for generation of two distinct Ultra-Wideband (UWB) signals and of two distinct Ultra-Narrowband (UNB) signals, wherein said two distinct UNB signals are missing cycle (MCY) Clock Shaped (CS) signals and further comprising an Ultra wideband (UWB) processor for processing a data signal into a third processed UWB signal, and said third processed UWB signal comprises a Time Constrained Signal (TCS) waveform shaped and Long Response (LR) filtered signal and further comprising a receiver for receiving and processing in said wireless device a Global Positioning System (GPS) generated signal into a GPS processed signal and for providing said GPS processed signal to said interface unit of said wireless device for use by said user of said wireless device and said two distinct UNB signals comprise Time Constrained Signal (TCS) waveform shaped and Long Response (LR) filtered signals.

10. The system of claim 3, further comprising a processor and modulator for processing and modulating said first and said second data signal into a missing cycle (MCY) modulated signal, wherein said MCY processed signal is a clock shaped signal and processing and modulating said first and said second data signal into a processed UNB phase reversal keying (PRK) modulated signal and further comprising a receiver for receiving and processing in said wireless device a Global Positioning System (GPS) generated signal into a GPS processed signal and for providing said GPS processed signal to said interface unit of said wireless device for use by said user of said wireless device.

* * * * *