



US010145954B2

(12) **United States Patent**
Davis et al.

(10) **Patent No.:** **US 10,145,954 B2**
(45) **Date of Patent:** **Dec. 4, 2018**

(54) **SOFTWARE DEFINED AUTOMOTIVE RADAR SYSTEMS**

(71) Applicant: **UHNDER, INC.**, Austin, TX (US)

(72) Inventors: **Curtis Davis**, St. Louis, MO (US); **Monier Maher**, St. Louis, MO (US); **Jean P. Bordes**, St. Charles, MO (US); **Manju Hegde**, St. Louis, MO (US); **Otto A. Schmid**, Morgantown, WV (US); **Raghunath K. Rao**, Austin, TX (US); **Marius Goldenberg**, Austin, TX (US); **Aria Eshraghi**, Austin, TX (US); **Vito Giannini**, Austin, TX (US); **David S. Trager**, Buda, TX (US); **Nikhilesh Bhagat**, Austin, TX (US); **Srikanth Gollapudi**, Austin, TX (US); **Sundar Govindarajan**, Chennai (IN); **Steve Borho**, St. Charles, MO (US); **Jonathan Preussner**, Austin, TX (US); **Paul W. Dent**, Pittsboro, NC (US); **Paul Bassett**, Austin, TX (US); **Stephen W. Alland**, Newbury Park, CA (US); **Fred Harris**, Lemon Grove, CA (US); **Wayne E. Stark**, Ann Arbor, MI (US); **Murtaza Ali**, Cedar Park, TX (US)

(73) Assignee: **Uhnder, Inc.**, Austin, TX (US)

(*) Notice: Subject to any disclaimer, the term of this patent is extended or adjusted under 35 U.S.C. 154(b) by 0 days.

(21) Appl. No.: **15/844,994**

(22) Filed: **Dec. 18, 2017**

(65) **Prior Publication Data**

US 2018/0100918 A1 Apr. 12, 2018

Related U.S. Application Data

(63) Continuation of application No. 15/496,313, filed on Apr. 25, 2017, now Pat. No. 9,846,228, which is a (Continued)

(51) **Int. Cl.**
G01S 13/93 (2006.01)
G01S 7/02 (2006.01)
(Continued)

(52) **U.S. Cl.**
CPC **G01S 13/931** (2013.01); **G01S 7/023** (2013.01); **G01S 13/87** (2013.01); **G01S 13/878** (2013.01);
(Continued)

(58) **Field of Classification Search**
CPC G01S 13/584; G01S 7/352
(Continued)

(56) **References Cited**
U.S. PATENT DOCUMENTS

1,882,128 A 10/1932 Fearing
3,374,478 A 3/1968 Blau
(Continued)

FOREIGN PATENT DOCUMENTS

EP 0725480 11/2011
EP 2374217 4/2013
(Continued)

OTHER PUBLICATIONS


Chambers et al., An article entitled "Real-Time Vehicle Mounted Multistatic Ground Penetrating Radar Imaging System for Buried Object Detection," Lawrence Livermore National Laboratory Reports (LLNL-TR-615452), Feb. 4, 2013; Retrieved from the Internet from <https://e-reports-ext.llnl.gov/pdf/711892.pdf>.
(Continued)

Primary Examiner — Marcus E Windrich

(74) *Attorney, Agent, or Firm* — Gardner, Linn, Burkhardt, & Ondersma, LLP

(57) **ABSTRACT**

A radar system processes signals in a flexible, adaptive manner to determine range, Doppler (velocity) and angle of objects in an environment. The radar system processes the (Continued)



received signal to achieve different objectives depending on one or more of a selected range resolution, a selected velocity resolution, and a selected angle of arrival resolution, as defined by memory requirements and processing requirements. The system allows improved resolution of range, Doppler and/or angle depending on the memory requirements and processing requirements.

21 Claims, 15 Drawing Sheets

Related U.S. Application Data

continuation-in-part of application No. 15/481,648, filed on Apr. 7, 2017, now Pat. No. 9,689,967.

- (60) Provisional application No. 62/327,003, filed on Apr. 25, 2016, provisional application No. 62/327,005, filed on Apr. 25, 2016, provisional application No. 62/327,018, filed on Apr. 25, 2016, provisional application No. 62/327,016, filed on Apr. 25, 2016, provisional application No. 62/327,004, filed on Apr. 25, 2016, provisional application No. 62/327,017, filed on Apr. 25, 2016, provisional application No. 62/327,015, filed on Apr. 25, 2016, provisional application No. 62/327,006, filed on Apr. 25, 2016, provisional application No. 62/327,003, filed on Apr. 25, 2016, provisional application No. 62/319,613, filed on Apr. 7, 2016.

(51) **Int. Cl.**

- G01S 13/87* (2006.01)
- H04L 27/227* (2006.01)
- G01S 7/35* (2006.01)
- H04B 17/309* (2015.01)
- H04B 17/345* (2015.01)

(52) **U.S. Cl.**

- CPC *H04L 27/2278* (2013.01); *G01S 2007/356* (2013.01); *G01S 2013/936* (2013.01); *G01S 2013/9357* (2013.01); *G01S 2013/9375* (2013.01); *G01S 2013/9378* (2013.01); *H04B 17/309* (2015.01); *H04B 17/345* (2015.01)

(58) **Field of Classification Search**

USPC 342/70–72
See application file for complete search history.

(56)

References Cited

U.S. PATENT DOCUMENTS

3,735,398 A 5/1973 Ross
3,750,169 A 7/1973 Strenglein
3,896,434 A 7/1975 Sirven
4,078,234 A 3/1978 Fishbein et al.
4,176,351 A 11/1979 De Vita et al.
4,566,010 A 1/1986 Collins
4,882,668 A 11/1989 Schmid et al.
4,910,464 A 3/1990 Trett et al.
4,939,685 A 7/1990 Feintuch
5,001,486 A 3/1991 Bächtiger
5,034,906 A 7/1991 Chang
5,087,918 A 2/1992 May et al.
5,151,702 A 9/1992 Urkowitz
5,175,710 A 12/1992 Hutson
5,218,619 A 6/1993 Dent
5,272,663 A 12/1993 Jones et al.
5,280,288 A 1/1994 Sherry et al.
5,302,956 A 4/1994 Asbury et al.
5,341,141 A 8/1994 Frazier et al.

5,345,470 A 9/1994 Alexander
5,376,939 A 12/1994 Urkowitz
5,379,322 A 1/1995 Kosaka et al.
5,497,162 A 3/1996 Kaiser
5,508,706 A 4/1996 Tsou et al.
5,657,021 A 8/1997 Ehsani-Nategh et al.
5,657,023 A 8/1997 Lewis et al.
5,712,640 A 1/1998 Andou
5,724,041 A 3/1998 Inoue et al.
5,892,477 A 4/1999 Wehling
5,917,430 A 6/1999 Greneker, III et al.
5,920,285 A 7/1999 Benjamin
5,931,893 A 8/1999 Dent et al.
5,959,571 A 9/1999 Aoyagi et al.
5,970,400 A 10/1999 Dwyer
6,067,314 A 5/2000 Azuma
6,069,581 A 5/2000 Bell et al.
6,121,872 A 9/2000 Weishaupt
6,121,918 A 9/2000 Tullsson
6,151,366 A 11/2000 Yip
6,163,252 A 12/2000 Nishiwaki
6,184,829 B1 2/2001 Stilp
6,191,726 B1 2/2001 Tullsson
6,288,672 B1 9/2001 Asano et al.
6,307,622 B1 10/2001 Lewis
6,347,264 B2 2/2002 Nicosia et al.
6,400,308 B1 6/2002 Bell et al.
6,411,250 B1 6/2002 Oswald et al.
6,417,796 B1 7/2002 Bowlds
6,424,289 B2 7/2002 Fukae et al.
6,583,753 B1 6/2003 Reed
6,614,387 B1 9/2003 Deadman
6,624,784 B1 9/2003 Yamaguchi
6,674,908 B1 1/2004 Aronov
6,714,956 B1 3/2004 Liu et al.
6,747,595 B2 6/2004 Hirabe
6,768,391 B1 7/2004 Dent et al.
6,865,218 B1 3/2005 Sourour
6,975,246 B1 12/2005 Trudeau
7,119,739 B1 10/2006 Struckman
7,289,058 B2 10/2007 Shima
7,299,251 B2 11/2007 Skidmore et al.
7,338,450 B2 3/2008 Kristofferson et al.
7,395,084 B2 7/2008 Anttila
7,460,055 B2 12/2008 Nishijima et al.
7,474,258 B1 1/2009 Arian et al.
7,545,310 B2 6/2009 Matsuoka
7,545,321 B2 6/2009 Kawasaki
7,564,400 B2 7/2009 Fukuda
7,567,204 B2 7/2009 Sakamoto
7,609,198 B2 10/2009 Chang
7,642,952 B2 1/2010 Fukuda
7,663,533 B2 2/2010 Toennesen
7,728,762 B2 6/2010 Sakamoto
7,791,528 B2* 9/2010 Klotzbuecher G01S 13/584
342/109
7,847,731 B2 12/2010 Wiesbeck et al.
7,855,677 B2 12/2010 Negoro et al.
7,859,450 B2 12/2010 Shirakawa et al.
8,019,352 B2 9/2011 Rappaport et al.
8,049,663 B2 11/2011 Frank et al.
8,059,026 B1 11/2011 Nunez
8,102,306 B2 1/2012 Smith, Jr. et al.
8,154,436 B2 4/2012 Szajnowski
8,330,650 B2 12/2012 Goldman
8,390,507 B2 3/2013 Wintermantel
8,471,760 B2 6/2013 Szajnowski
8,532,159 B2 9/2013 Kagawa et al.
8,547,988 B2 10/2013 Hadani et al.
8,686,894 B2 4/2014 Fukuda et al.
8,694,306 B1 4/2014 Short et al.
9,121,943 B2 9/2015 Stirlin-Gallacher et al.
9,239,378 B2 1/2016 Kishigami et al.
9,239,379 B2 1/2016 Burgio et al.
9,282,945 B2 3/2016 Smith et al.
9,335,402 B2 5/2016 Maeno et al.
9,541,639 B2 1/2017 Searcy et al.
9,568,600 B2 2/2017 Alland
9,575,160 B1 2/2017 Davis et al.

(56)		References Cited					
U.S. PATENT DOCUMENTS							
9,599,702	B1	3/2017	Bordes et al.	2009/0267822	A1	10/2009	Shinoda et al.
9,689,967	B1	6/2017	Stark et al.	2009/0289831	A1	11/2009	Akita
9,720,073	B1	8/2017	Davis et al.	2009/0295623	A1	12/2009	Falk
9,753,121	B1	9/2017	Davis	2010/0019950	A1	1/2010	Yamano et al.
9,753,132	B1	9/2017	Bordes et al.	2010/0116365	A1	5/2010	McCarty
9,772,397	B1	9/2017	Bordes et al.	2010/0156690	A1	6/2010	Kim et al.
9,791,551	B1	10/2017	Eshraghi et al.	2010/0198513	A1	8/2010	Zeng et al.
9,791,564	B1	10/2017	Harris et al.	2010/0277359	A1	11/2010	Ando
9,806,914	B1	10/2017	Bordes et al.	2011/0006944	A1	1/2011	Goldman
9,829,567	B1	11/2017	Davis et al.	2011/0032138	A1	2/2011	Krapf
9,846,228	B2	12/2017	Davis et al.	2011/0074620	A1	3/2011	Wintermantel
9,869,762	B1	1/2018	Alland et al.	2011/0187600	A1	8/2011	Landt
2001/0002919	A1	6/2001	Sourour et al.	2011/0196568	A1	8/2011	Nickolaou
2002/0004692	A1	1/2002	Nicosia et al.	2011/0248796	A1	10/2011	Pozgay
2002/0044082	A1	4/2002	Woodington et al.	2011/0279303	A1	11/2011	Smith, Jr. et al.
2002/0075178	A1	6/2002	Woodington et al.	2011/0279307	A1	11/2011	Song
2002/0118522	A1	8/2002	Ho et al.	2011/0285576	A1	11/2011	Lynam
2002/0130811	A1	9/2002	Voigtlaender	2011/0291874	A1	12/2011	De Mersseman
2002/0147534	A1	10/2002	Delcheccolo et al.	2011/0291875	A1	12/2011	Szajnowski
2002/0155811	A1	10/2002	Prismantas	2011/0292971	A1	12/2011	Hadani et al.
2003/0001772	A1	1/2003	Woodington et al.	2012/0001791	A1	1/2012	Wintermantel
2003/0011519	A1	1/2003	Breglia et al.	2012/0050093	A1	3/2012	Heilmann et al.
2003/0058166	A1	3/2003	Hirabe	2012/0105268	A1	5/2012	Smits et al.
2003/0102997	A1	6/2003	Levin et al.	2012/0112957	A1	5/2012	Nguyen et al.
2003/0235244	A1	12/2003	Pessoa et al.	2012/0133547	A1	5/2012	MacDonald et al.
2004/0012516	A1	1/2004	Schiffmann	2012/0173246	A1	7/2012	Choi et al.
2004/0015529	A1	1/2004	Tanrikulu et al.	2012/0195349	A1	8/2012	Lakkis
2004/0066323	A1	4/2004	Richter	2012/0257643	A1	10/2012	Wu et al.
2004/0138802	A1	7/2004	Kuragaki et al.	2012/0319900	A1	12/2012	Johansson et al.
2005/0069162	A1	3/2005	Haykin	2013/0016761	A1	1/2013	Nentwig
2005/0156780	A1	7/2005	Bonthron et al.	2013/0021196	A1	1/2013	Himmelstoss
2005/0201457	A1	9/2005	Allred et al.	2013/0027240	A1	1/2013	Chowdhury
2005/0225476	A1	10/2005	Hoetzel et al.	2013/0069818	A1	3/2013	Shirakawa et al.
2006/0012511	A1	1/2006	Dooi et al.	2013/0102254	A1	4/2013	Cyzs
2006/0036353	A1	2/2006	Wintermantel	2013/0113653	A1	5/2013	Kishigami et al.
2006/0050707	A1	3/2006	Sterin	2013/0135140	A1	5/2013	Kishigami
2006/0093078	A1	5/2006	Lewis et al.	2013/0169485	A1	7/2013	Lynch
2006/0109170	A1	5/2006	Voigtlaender et al.	2013/0176154	A1	7/2013	Bonaccio et al.
2006/0109931	A1	5/2006	Asai	2013/0214961	A1	8/2013	Lee et al.
2006/0114324	A1	6/2006	Farmer et al.	2013/0229301	A1	9/2013	Kanamoto
2006/0140249	A1	6/2006	Kohno	2013/0244710	A1	9/2013	Nguyen et al.
2006/0181448	A1	8/2006	Natsume et al.	2013/0249730	A1	9/2013	Adcook
2006/0244653	A1	11/2006	Szajnowski	2013/0314271	A1	11/2013	Braswell et al.
2006/0262007	A1*	11/2006	Bonthron	2013/0321196	A1	12/2013	Binzer et al.
		 G01S 13/34	2014/0022108	A1	1/2014	Alberth, Jr. et al.
			342/70	2014/0028491	A1	1/2014	Ferguson
				2014/0035774	A1	2/2014	Khlifi
				2014/0070985	A1	3/2014	Vacanti
				2014/0085128	A1	3/2014	Kishigami et al.
				2014/0111372	A1	4/2014	Wu
				2014/0139322	A1	5/2014	Wang et al.
				2014/0159948	A1	6/2014	Ishimori et al.
				2014/0220903	A1	8/2014	Schulz et al.
				2014/0253345	A1	9/2014	Breed
				2014/0285373	A1	9/2014	Kuwahara et al.
				2014/0327566	A1	11/2014	Burgio et al.
				2014/0348253	A1	11/2014	Mobasher et al.
				2015/0002329	A1	1/2015	Murad et al.
				2015/0002357	A1	1/2015	Sanford et al.
				2015/0035662	A1	2/2015	Bowers et al.
				2015/0061922	A1	3/2015	Kishigami
				2015/0103745	A1	4/2015	Negus et al.
				2015/0198709	A1	7/2015	Inoue
				2015/0204966	A1	7/2015	Kishigami
				2015/0204971	A1	7/2015	Kuehnle
				2015/0226848	A1	8/2015	Park
				2015/0234045	A1*	8/2015	Rosenblum
		 G01S 13/931				342/71
				2015/0247924	A1	9/2015	Kishigami
				2015/0255867	A1	9/2015	Inoue
				2015/0301172	A1	10/2015	Ossowska
				2015/0323660	A1	11/2015	Hampikian
				2015/0331090	A1	11/2015	Jeong et al.
				2016/0003939	A1	1/2016	Stainvas Olshansky et al.
				2016/0018511	A1	1/2016	Nayyar et al.
				2016/0033631	A1	2/2016	Searcy et al.
				2016/0033632	A1	2/2016	Searcy et al.
				2016/0041260	A1	2/2016	Cao et al.
				2016/0061935	A1	3/2016	McCloskey et al.
2007/0018884	A1	1/2007	Adams				
2007/0018886	A1	1/2007	Watanabe et al.				
2007/0109175	A1	5/2007	Fukuda				
2007/0120731	A1	5/2007	Kelly, Jr. et al.				
2007/0132633	A1	6/2007	Uchino				
2007/0152870	A1	7/2007	Woodington et al.				
2007/0152871	A1	7/2007	Puglia				
2007/0152872	A1	7/2007	Woodington				
2007/0164896	A1	7/2007	Suzuki et al.				
2007/0171122	A1	7/2007	Nakano				
2007/0182619	A1	8/2007	Honda et al.				
2007/0182623	A1	8/2007	Zeng				
2007/0188373	A1	8/2007	Shirakawa et al.				
2007/0200747	A1	8/2007	Okai				
2007/0279303	A1	12/2007	Schoebel				
2008/0208472	A1	8/2008	Morcom				
2008/0272955	A1	11/2008	Yonak et al.				
2009/0015459	A1	1/2009	Mahler et al.				
2009/0015464	A1	1/2009	Fukuda				
2009/0051581	A1	2/2009	Hatono				
2009/0072957	A1	3/2009	Wu et al.				
2009/0073025	A1	3/2009	Inoue et al.				
2009/0079617	A1	3/2009	Shirakawa et al.				
2009/0085827	A1	4/2009	Orime et al.				
2009/0103593	A1	4/2009	Bergamo				
2009/0121918	A1	5/2009	Shirai et al.				
2009/0212998	A1	8/2009	Szajnowski				
2009/0237293	A1	9/2009	Sakuma				

(56)

References Cited

U.S. PATENT DOCUMENTS

2016/0084941	A1	3/2016	Arage
2016/0084943	A1	3/2016	Arage
2016/0091595	A1	3/2016	Alcalde
2016/0124086	A1	5/2016	Jansen et al.
2016/0139254	A1	5/2016	Wittenberg
2016/0146931	A1	5/2016	Rao et al.
2016/0238694	A1	8/2016	Kishigami
2017/0023661	A1	1/2017	Richert
2017/0219689	A1	8/2017	Hung et al.
2017/0234968	A1	8/2017	Roger et al.
2017/0293025	A1	10/2017	Davis et al.
2017/0293027	A1	10/2017	Stark et al.
2017/0307728	A1	10/2017	Eshraghi et al.
2017/0309997	A1	10/2017	Alland et al.
2017/0310758	A1	10/2017	Davis et al.
2017/0336495	A1	11/2017	Davis et al.

FOREIGN PATENT DOCUMENTS

EP	2821808	7/2015
----	---------	--------

FR	2751086	1/1998
WO	WO2015175078	11/2015
WO	WO2015185058	12/2015
WO	WO2016011407	1/2016
WO	WO2016030656	3/2016
WO	WO2017175190	10/2017
WO	WO2017187330	11/2017

OTHER PUBLICATIONS

Fraser, "Design and simulation of a coded sequence ground penetrating radar," In: Diss. University of British Columbia, Dec. 3, 2015.

Zhou et al., "Linear extractors for extracting randomness from noisy sources," In: Information Theory Proceedings (ISIT), 2011 IEEE International Symposium on Oct. 3, 2011.

V. Giannini et al., "A 79 GHz Phase-Modulated 4 GHz-BW CW Radar Transmitter in 28 nm CMOS," in IEEE Journal of Solid-State Circuits, vol. 49, No. 12, pp. 2925-2937, Dec. 2014. (Year: 2014).

* cited by examiner




FIG. 1




FIG. 2A




FIG. 2B




FIG. 3




FIG. 4




FIG. 7




FIG. 9




FIG. 11b

FIGS. 11a, 11b, 11c, and 11d are block diagrams illustrating exemplary steps to signal processing in accordance with the present invention.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

The present invention will now be described with reference to the accompanying figures, wherein numbered elements in the following written description correspond to like-numbered elements in the figures. Methods and systems of the present invention may achieve better performance from a radar system when there is a near object and a far object. Exemplary embodiments of the present invention accomplish better performance by adjusting the radar system to the environment, the objective and inputs external to the radar system. The invention accomplishes better performance by adapting the radar system under software control.

The radar sensing system of the present invention may utilize aspects of the radar systems described in U.S. Pat. Nos. 9,575,160 and/or 9,599,702, and/or U.S. patent applications, Ser. No. 15/416,219, filed Jan. 26, 2017, now U.S. Pat. No. 9,772,397, and/or Ser. No. 15/292,755, filed Oct. 13, 2016, now U.S. Pat. No. 9,753,121, and/or U.S. provisional applications, Ser. No. 62/382,857, filed Sep. 2, 2016, and/or Ser. No. 62/381,808, filed Aug. 31, 2016, which are all hereby incorporated by reference herein in their entireties.

As illustrated in FIG. 1, there may be multiple radars (e.g., 104a-104d) embedded into an automobile. Each of these could employ the ideas contained in the present invention. FIG. 1 illustrates an exemplary radar system 100 configured for use in a vehicle 150. In an aspect of the present invention, a vehicle 150 may be an automobile, truck, or bus, etc. As illustrated in FIG. 1, the radar system 100 may comprise one or more transmitters and one or more virtual receivers 104a-104d, control and processing module 102 and indicator 106. Other configurations are also possible. FIG. 1 illustrates receivers/transmitters 104a-104d placed to acquire and provide data for object detection and adaptive cruise control. The radar system 100 (providing such object detection and adaptive cruise control or the like) may be part of an Advanced Driver Assistance System (ADAS) for the automobile 150.

A radar system operates by transmitting a signal and then listening for the reflection of that signal from objects in the environment. By comparing the transmitted signal and the received signal, estimates of the range to different objects, the velocity of different objects and the angle (azimuth and/or elevation) can be estimated.

There are several different types of signals that transmitters in radar systems employ. A radar system may transmit a continuous signal or a pulsed signal. In a pulsed radar system, the signal is transmitted for a short time and then no signal is transmitted. This is repeated over and over. When the signal is not being transmitted, the receiver listens for echoes or reflections from objects in the environment. Often a single antenna is used for both the transmitter and receiver and the radar transmits on the antenna and then listens to the received signal on the same antenna. This process is then repeated. In a continuous wave radar system, the signal is continuously transmitted. There may be an antenna for transmitting and a separate antenna for receiving. One type of continuous wave radar signal is known as frequency modulated continuous wave (FMCW) radar signal. In FMCW the transmitted signal is a sinusoidal signal with varying frequency. By measuring the time difference

between when a certain frequency was transmitted and when the received signal contained that frequency the range to an object can be determined.

A second type of continuous wave signal used in radar systems is a phase modulated continuous wave (PMCW) signal. In this type of radar system, the transmitted signal is a sinusoidal signal in which the phase of the sinusoidal signal varies. Typically, the phase during a given time period (called a chip period or chip duration) is one of a finite number of possible phases. A spreading code consisting of sequence of chips, (e.g., +1, +1, -1, +1, -1, . . .) that is mapped (e.g., +1 \rightarrow 0, -1 \rightarrow π) into a sequence of phases (e.g., 0, 0, π , 0, π , . . .) that is used to modulate a carrier to generate the radio frequency (RF) signal. The spreading code could be a periodic sequence or could be a pseudo-random sequence with a very large period so it appears to be a nearly random sequence. The spreading code could be a binary code (e.g., +1 or -1). The resulting signal has a bandwidth that is proportional to the rate at which the phases change, called the chip rate, which is the inverse of the chip duration. By comparing the return signal to the transmitted signal the receiver can determine the range and the velocity of reflected objects.

There are several ways to implement a radar system. One way, shown in FIG. 2A uses a single antenna 202 for transmitting and receiving. The antenna is connected to a duplexer 204 that routes the appropriate signal from the antenna to the receiver (208) or routes the signal from the transmitter 206 to the antenna 202. A control processor 210 controls the operation of the transmitter and receiver and estimates the range and velocity of objects in the environment. A second way to implement a radar system is shown in FIG. 2B. In this system, there are separate antennas for transmitting (202A) and receiving (202B). A control processor 210 performs the same basic functions as in FIG. 2A. In each case, there may be a display to visualize the location of objects in the environment.

A radar system with multiple antennas, transmitters and receivers is shown in FIG. 3. Using multiple antennas allows a radar system to determine the angle (azimuth or elevation or both) of targets in the environment. Depending on the geometry of the antenna system different angles (e.g., azimuth or elevation) can be determined.

The radar system may be connected to a network via an Ethernet connection or other types of network connections 314. The radar system will have memory (310, 312) to store software used for processing the signals in order to determine range, velocity and location of objects. Memory can also be used to store information about targets in the environment.

A basic block diagram of a PMCW system with a single transmitter and receiver is shown in FIG. 4. The transmitter 400, as shown in FIG. 4, consists of a digital signal generator 410, followed by a digital-to-analog converter (DAC) 420. The output of the DAC followed is up converted to a RF signal and amplified by the analog processing 430 unit. The result is then used as the antenna 440 input. The digital signal generator generates a baseband signal. The receiver, as shown in FIG. 4, consists of a receiving antenna 460, an analog processing unit that down amplifies the signal and mixes the signal to baseband 470. This is followed by an analog-to-digital converter (ADC) 480 and then digital baseband processing 490. There is also a control processor (not shown) that controls the operation of the transmitter and receiver. The baseband processing will process the received signal and may generate data that can be used to determine range, velocity and angle.

complex analog baseband signal is converted to a complex baseband digital signal by using analog-to-digital converters (ADCs) 480. The complex baseband digital signal (output by the ADCs 480) is then the input to a digital processing unit 490. The digital processing unit 490 performs correlations or matched filtering. The correlators multiply the received complex baseband signal by a delayed replica of the baseband transmitted signal and then the result is accumulated over a certain time interval. A bank of correlators where each correlator has a different delay used for the replica of the baseband transmitted signal will produce a set of correlations that correspond to different ranges of objects. In essence, a correlator that has a particular delay of the baseband transmitted signal is looking for the presence of a reflection from an object at a distance corresponding to the particular delay for the particular correlator, and for which the round-trip delay is the delay used for the baseband transmitted signal.

A matched filter is a device that produces all correlations for all possible delays. That is, the output of the matched filter at a given time corresponds to a correlation with a given delay applied to the transmitted signal when doing the correlation. The matched filter provides all possible correlations. Note that the matched filter should produce a complex output because the input is complex. Alternatively, there could be a filter for the real part of the input and a filter for the imaginary part of the input. A matched filter can also be implemented by a fast Fourier transform (FFT) of the received complex baseband signal and the corresponding transmitted signal, multiplying the results, and then taking an inverse fast Fourier transform (IFFT).

FIG. 5 illustrates a baseband signal which has a period of $L_C=31$. The chips in this example are from a maximal length sequence (m-sequence) of length $L_C=31$ generated by an exemplary shift register of length 5. Note that the signal repeats every L_C chips or $L_C T_C$ seconds. The pulse repetition rate is $R_{PR}=1/(L_C T_C)$. The transmitted signal is generated from the baseband signal by modulating the baseband signal onto a carrier frequency to generate a radio frequency signal.

FIG. 6 shows the real part of the output of a matched filter due to the transmitted baseband signal shown in FIG. 5. Here it is assumed the radar started to transmit at time 0 and there is no delay between the transmitter and receiver. That is, there is an object at distance 0. The matched filter output before a full period of the signal is transmitted generates partial correlations. That is, it correlates with only a portion of the code because only a portion of the code has been transmitted. Only after the entire period of the code has been transmitted does the correlation reach a peak. In continuous operation, an object that has a delay of one period of the spreading code will appear to have the same delay as an object at distance 0. Thus, a radar using this system cannot determine whether the delay is 0, one period of the spreading code, two periods of the spreading code, and so on. Therefore, the maximum unambiguous range in this case corresponds to at most one period of the spreading code. A longer spreading code will yield a larger maximum unambiguous range. A delay of τ corresponds to a range of $\tau c/2$ where c is the speed of light. The factor of two is because the delay corresponds to the round-trip time from the radar to the target and back to the radar. Here the assumption is that the transmitter and receiver are approximately co-located.

FIG. 7 illustrates the real part of the output of the matched filter when there are two objects that have a differential range delay of 2 chip durations. The filter output shows two distinct peaks in the output of the matched filter.

For PMCW radar systems that utilize nonideal spreading codes and correlate over a certain time interval, the auto-correlation is not ideal. That is, the sidelobes are not zero. The sidelobes of a near target can mask the peak of the correlation for a far object or target because the signal from the near object or target is far stronger than the signal from the far object or target.

Range Estimation

FIG. 8 illustrates the case where the differential round trip delay between two targets is one chip duration. In this case, two objects cannot be distinguished and thus the range resolution of this would correspond to the differential distance corresponding to a duration of half ($1/2$) a chip. If T_c denotes the chip duration and L_c denotes the number of chips in one period of the transmitted sequence, then the rate at which the sequence is repeated is $R_{PR}=1/(L_c T_c)$, which is sometimes referred to as the pulse repetition rate even though this is a continuous type of signal. If c denotes the speed of light, then the range resolution is given by:

$$D_R=(T_c/2)c=c/(2R_{PR} L_c).$$

If a signal repeats every T_{PR} or at rate R_{PR} , then the maximum unambiguous range D_U is:

$$D_U=cT_{PR}/2=(c T_c L_c)/2=c/(2R_{PR}).$$

Two targets separated by the maximum unambiguous range will appear to the radar systems as being at the same range. This is sometimes called range aliasing. If the chip duration, T_c , is decreased, then the range resolutions would improve proportionally. However, changing the chip duration changes the bandwidth, which might be limited by regulations. If there are 31 chips per period of the spreading code, there are at most 31 different ranges that can be distinguished. As an example, if $T_c=10$ nanoseconds (a chip rate of 100 Mchips/second), then the range resolution would be limited to 1.5 meters. That is, two objects separated by less than 1.5 m would cause reflected signals to be less than a chip duration apart in delay. For this example, the maximum unambiguous range would be 46.5 m. That is, an object at a distance of 46.5 m would cause a reflected signal to have a delay exactly equal to the period of the signal and thus would appear as an object at a distance of 0 m. A longer spreading code would provide for a larger unambiguous range. For example, a spreading code of length 1023 would provide a maximum unambiguous range of about 1,534 m.

Velocity Estimation

Another goal of an exemplary radar system is to estimate the differential velocity between the radar system and a target. Because targets in the environment, or the radar itself, are moving, the signal reflected from an object will not have the same frequency as the transmitted signal. This effect is known as the Doppler Effect and can be used to determine the relative velocity of targets in the environment. Suppose the differential (radial) velocity of the target relative to the radar system is Δv and the carrier frequency is f_c . Then, the Doppler frequency shift is $f_D=2\Delta v f_c/c$. This is because there is a Doppler shift of $\Delta v f_c/c$ between the radar transmitter and the target and then an additional $\Delta v f_c/c$ Doppler shift of the reflected signal from the target to the radar receiver. For example, a carrier frequency of 79 GHz with a differential velocity of 300 km/hour =83.3 m/s would result in a frequency shift of about 44 kHz. A frequency shift of f_D corresponds to a differential velocity of $\Delta v=(f_D)(c)/(2 f_c)$.

Suppose that a signal, for example an m-sequence, is repeated N times. This is called a scan. The period of the signal is $L_c T_c$. The time duration of the scan is $N L_c T_c$. During each repetition, a correlation with a spreading code

11

nonstationary objects are rather sparse in the environment. These characteristics can be exploited in processing the data obtained from the signals received from objects in the environment.

In addition to the above, interference from other radar systems needs to be accounted for. Interfering radars could be using the same type of signals as the vehicle in which the invention of this patent is installed. It is also possible that the interfering radar system is using a different type of signal (e.g., FMCW vs. PMCW). It would be useful to be able to mitigate in some way the effect of interfering radar systems. Different types of interference will require different mitigation techniques. Mitigation of the effects of interfering systems generally will not be ideal and it is often the case that the mitigation, while reducing the effect of the interference, will also degrade the desired signal in some manner. If no interfering radar system is present, then it would be desirable to not employ the mitigation technique. As such, it would be desirable to have a radar system that can adapt to the environment present.

In a preferred embodiment, the processing of the signals is shown in FIGS. 11a, 11b, 11c, and 11d. FIG. 11a illustrates exemplary processing modules for a transmitter. A code generator 1102 generates a spreading code. The output of the code generator 1102 is modulated with a digital modulator 1104 to generate a complex baseband signal. The modulation is accomplished in two parts. In the first part the code is mapped to a complex sequence of in-phase and quadrature phase components at the digital modulator 1104. The result is converted to an analog signal by the digital-to-analog converter (DAC) 1106. The output is further shaped with a pulse shaper 1108 to generate a complex baseband analog signal. This signal is up-converted with a TX Mixer 1110. An oscillator 1124 is the other input to the mixer to produce a radio frequency (RF) signal. The oscillator signal is also used at the receiver. This is indicated by the connection of the oscillator to components in FIG. 11b. The result of up-conversion is then amplified by a power amplifier 1120 before transmission by an antenna 1122. A master clock 1126 is used to control the timing of the oscillator and to control the timing of the digital circuitry. The master clock 1126 and the oscillator are also shared with the transmitter circuitry shown in FIGS. 11b and 11c. The output of the digital modulator 1104 is shared with the receiver so that the receiver can apply interference cancellation. The output of the code generator 1102 is shared from the transmitter to receiver so appropriate correlation or matched filtering can be applied at the receiver.

FIG. 11b illustrates exemplary analog processing circuitry of the receiver. Various blocks or modules are illustrated. One or more receiving antennas are connected to a switch 1142 that connects one of the antennas 1140 to a receiver. There can be more than one receiver so that different antennas can be connected to different receivers. Not all the antennas need to be connected to a receiver. Because there can be very strong self-interference from the transmitted signal reflecting off of nearby objects (e.g., a bumper), the analog interference cancellation unit 1146 is employed. A signal from the cancellation unit 1146 can be provided to the digital processing where additional interference cancellation can be done. The output of the analog interference cancellation 1146 is provided to a low noise amplifier 1148. The low noise amplifier output is mixed down to baseband by an RF mixer that also uses the oscillator signal (from FIG. 11a). The resulting low pass complex baseband analog signal is filtered (with low pass filter 1152), and further amplified (with gain control 1154) before being converted to a digital

12

signal by an analog-to-digital converter (ADC) 1156. The result of the ADC 1156 is fed to digital processing circuitry shown in FIG. 11c.

FIG. 11c illustrates exemplary digital processing circuitry of the receiver. Various signal processing blocks or modules are illustrated. First, a saturation detection block 1160 detects whether the ADC input has caused the ADC 1156 to saturate. This detection can be used to adjust the gain in the gain control 1154. Next, a change in the sample rate can be performed (1162) to reduce the amount of processing necessary. After resampling, correction for any mismatch in I, Q gain or non-orthogonality can be employed (via I/O Correction module 1164). Additional interference can be cancelled in a digital interference canceller 1166. Information from the processing done by the analog cancellation unit 1146 can be used (as shown by the connection from FIG. 11b) by the digital interference cancellation unit 1166. This can more accurately (as compared to the analog interference canceller 1146) remove interference from near targets, including the bumper. Further interference cancellation (with large target canceller 1168) can be done to minimize the effect of sidelobes of a near target on the detectability of a further target. Interference from other radar systems, such as an FMCW system, can also be incorporated (such as FMCW/Tone Canceller 1170) into the digital processing. The resulting information is stored in a buffer 1174. This allows all digital processing to be suspended temporarily in order to not create unwanted radio frequency interference from the digital processing. Finally, the signal is processed by correlating with a correlator 1176, with delayed versions of the code from the code generator (1102). The correlator(s) 1176 could be implemented in a number of ways including a matched filter and an FFT-based approach. The samples of the output of the correlator or matched filter (1176) are stored in memory as radar data cubes (RDC), such as RDC1 (1178). The correlation values for different delays, different receivers, and different times are stored in the radar data cube. The information from RDC1 is processed further to determine object velocity and angle (e.g., azimuth or elevation or both). The information from the correlators for one scan may be stored in different parts of the radar data cube so that data can be written in one part of the memory RDC1 and used for Doppler and angle processing while other parts of the memory corresponding to different scans are being read for Doppler and angle processing. The sizes of these different parts of the memory can be different, corresponding to different performance objectives. Further software control of the processing of information stored in RDC1 may be performed to determine the velocity of targets.

FIG. 11d illustrates the back-end digital processing. The front-end analog and digital processing, illustrated in FIGS. 11a-c, processes the received signal and stores the processed information (complex signals) in the radar data cube 1 (RDC1). The information is related to signals reflected from objects as a function of time (one of the dimensions) at various distances (a second dimension) and for various receivers (a third dimension). Information from various receivers is stored in a common memory. To determine the velocity of an object, a particular "slice" of the radar data cube is processed. A slice of a cube refers to a two-dimensional subset of the data where one of the variables (either range, time, or receiver) is fixed. Processing can also be done on the information with the range and Doppler fixed. In this case, the data is one dimensional and is known as a skewer. The slice of RDC1 where range is fixed, and the virtual receiver is fixed, but the sequence of correlation values for different times are varied, can be used to calculate

phased array radar system, that must be stored to memory for performing subsequent processing. The method comprises the steps of:

Performing spatial windowing and beamforming (e.g., delay and sum) on one or more input (complex) sample vectors from RDC2 for a given range and Doppler for various virtual receivers to produce output complex sample vectors (RDC3) for the corresponding range and Doppler and angle.

The control processor identifies a region of samples in RDC3. In a preferred embodiment, this region corresponds to a band of low absolute velocity that includes ground clutter.

Samples of RDC3 in the identified band are stored in a separate memory buffer called a static slice. The samples in the identified band are tagged as being included in the static slice. The complete set of RDC3 samples are processed by a decimator/sparsifier.

For each untagged sample in RDC3, the decimator/sparsifier compares the magnitude of the sample to one or more thresholds configured by the control processor. Depending on the outcome of the comparison, a set of samples, including the sample, are stored in one of one or more distinct memory buffers. Preferably, the set of samples are samples with similar Doppler, range and/or angle (azimuth and/or elevation). In the preferred embodiment, the set includes all samples with the same range and Doppler. These buffers are called the sparsified RDC3 (sRDC3). In a preferred embodiment, different thresholds may be configured for different range bins. In another preferred embodiment, the thresholds are determined by analyzing histograms of RDC3 sample magnitudes. Different histograms may be computed for different subsets of RDC3 (e.g., one histogram per range bin).

The samples stored in the static slice or the sparsified RDC3 (sRDC3) may be stored as complex numbers (real and imaginary part), magnitude only, or both. Which mechanism to store is determined by the control processor.

The above steps of processing are controlled by the control processor in order to achieve the performance objectives.

Asynchronous, Parallel, Memory Efficient MUSIC Engine:

The present invention provides a method and device for performing adaptive on-demand super resolution angle-of-arrival (AoA) processing on a subset of the range, Doppler, angle space (i.e., a subset of RDC3), comprising the steps of:

Using a control processor to analyze the static slice and sRDC3 to identify regions of interest. In a preferred embodiment, the region of interest is a local maximum of the magnitude of the samples. The control processor tracks regions of interest over time including multiple scans.

Using a control processor to choose a subset of range, Doppler, angle space based on past and current samples of the static slice and/or sRDC3 in the regions of interest, in which to perform super resolution angle of arrival processing.

Using a control processor to select a subset of the range bins of RDC1 on which to perform Doppler processing. In the preferred embodiment, the Doppler processing is performed by a channelizer. Using a control processor to select a subset of the Doppler bins (channels) to perform super resolution processing.

Using a control processor to configure a MUSIC engine to provide super resolution processing on the subset of range, Doppler, and angle space. In preferred embodi-

ment, the configuration includes spatial smoothing steps, parameters for singular value decomposition (SVD) calculation (e.g., a maximum number of iterations and precision threshold), an estimated number of signal eigenvectors, and steering vector matrix). In the preferred embodiment, the control processor configures the MUSIC engine by providing commands and parameters through a FIFO.

Using a MUSIC (MULTiple Signal Classification) Engine configured by the control processor to determine location of peaks in the angular dimension for the specified subset of range, Doppler, and angle space, comprising the steps of:

Calculating a sample covariance matrix from one or more samples of input data.

Performing spatial smoothing on the covariance matrix. Calculating the singular value decomposition of the covariance matrix.

Using the singular values to estimate the number of signals.

Using a sub-matrix of the left unitary matrix (representing the noise subspace) to compute the MUSIC spectrum over a specified range of angles.

Writing to an output FIFO a list of angles corresponding to peaks of the MUSIC spectrum occurring in the specified range of angle.

Compressing Range Bins Dynamically and Adaptively (Variable Range Bins):

In case of a PMCW-based radar system, range bins are used to identify how far objects are from the radar. The range bin resolution is usually linear, which means if the range bin resolution is 0.1 m, then 900 range bins are required for a distance of 10-100 m. This results in a large radar cube overhead. The larger the distance, the larger can be the range resolution. The range bins can be compressed, assuming for example that the range resolution can be 1 percent of the distance, which means at 10 m the range resolution is 0.1 m, at 20 m it is 0.2 m, at 30 m it is 0.3 m, and so on. If variable range bins are used, several range bins can be combined to a single range bin when the object is far away, thereby effectively reducing the total number of required range bins.

This approach can also be used to reduce the number of total range bins if object locations are known or object positions are being tracked. Assume for example, that the range between 10-100 m is using a range resolution of 2.5 m, which implies 36 range bins. And as soon as a range bin contains objects to be tracked, only that quadrant is used, with higher resolution range bins. The present invention uses a control processor to configure the resolution around tracked objects with much higher resolution compared to the areas without objects.

The system thus has reduced memory requirements by compressing several range bins into a single range bin using a configurable variable range bin parameter on a per range bin basis. Care is needed prior to aggregating range bins as the SNR will be negatively impacted. For close objects and near empty ranges, this is likely a good trade off. The control processor controls the ranges and resolutions that are correlated with by the pipeline processing.

Changes and modifications in the specifically described embodiments can be carried out without departing from the principles of the invention, which is intended to be limited only by the scope of the appended claims, as interpreted according to the principles of patent law including the doctrine of equivalents.

21

operation of at least one device selected from the group consisting of (i) a receive antenna of the receiver, (ii) an analog processing unit of the receiver, (iii) an analog-to-digital converter of the receiver, (iv) a digital front end processing unit of the receiver, and (v) a digital back end processing system of the receiver.

12. The radar sensing system of claim 8, wherein the control unit is configured to control an operation of the receiver to process range information from the received radio signals, and wherein the receiver is configured to:

identify a set of objects with a highest received signal strength;

estimate a Doppler velocity for the objects using one of a median, a weighted arithmetic mean, and a weighted geometric mean of corresponding samples for different range bins associated with an object;

calculate one of (i) a first phase shift, from one complex correlator input sample to a next complex correlator input sample, that corresponds to the estimated Doppler velocity, and (ii) a second phase shift, from one complex correlator output sample to a next complex correlator output sample, that corresponds to the estimated Doppler velocity; and

derotate an Nth complex sample pre or post correlator by a multiple of one of the first phase shift and the second phase shift, depending on which phase shift was estimated.

13. The radar sensing system of claim 8, wherein the control unit is configured to control an operation of the receiver to process range information from the received radio signals, and wherein the receiver is configured to:

select an object for which a better Doppler estimation is desired;

store multiple time scans corresponding to a range of a desired object; and

perform Doppler processing on extended information from multiple scans to obtain more precise Doppler information.

14. The radar sensing system of claim 8, wherein the control unit is configured to control an operation of at least one of the transmitter and the receiver based upon external information received by the radar sensing system.

15. A radar sensing system for a vehicle, the radar sensing system comprising:

a plurality of transmitters configured for installation and use on a vehicle, and configured to transmit radio signals;

a plurality of receivers configured for installation and use on the vehicle, and configured to receive radio signals, wherein the received radio signals include transmitted radio signals transmitted by the plurality of transmitters and reflected from objects in an environment;

a memory;

a control unit configured to control an operation of at least one of the plurality of transmitters and the plurality of receivers based upon at least one of memory requirements and processing time requirements, wherein the control unit is configured to dynamically and adaptively vary the operation of at least one of the transmitter and the receiver, as defined by a selected functional requirement and a current environmental condition, and wherein the control unit is further configured to adjust a radar data compression rate of the radar sensing system based upon one of a selected processing time and a memory requirement;

wherein data produced by the plurality of receivers from the received radio signals is stored in the memory; and

22

wherein the control unit controls the processing of the stored data based upon the controlled operation of the at least one of the plurality of transmitters and the plurality of receivers.

16. A radar sensing system for a vehicle, the radar sensing system, comprising:

a plurality of transmitters configured for installation and use on a vehicle, and configured to transmit radio signals;

a plurality of receivers configured for installation and use on the vehicle, and configured to receive radio signals, wherein the received radio signals include transmitted radio signals transmitted by the plurality of transmitters and reflected from objects in an environment;

a memory;

a control unit configured to control operation of at least one of the plurality of transmitters and the plurality of receivers based upon at least one of memory requirements and processing requirement, wherein the control unit is further configured to dynamically and adaptively vary the operation of at least one of the transmitter and the receiver, as defined by a selected functional requirement and a current environmental condition, wherein controlling an operation of at least one of the plurality of receivers comprises compressing one or more range bins dynamically and adaptively to achieve a selected memory requirement;

wherein data produced by the plurality of receivers from the received radio signals is stored in the memory; and wherein the control unit controls the processing of the stored data based upon the controlled operation of the at least one of the plurality of transmitters and the plurality of receivers.

17. The radar sensing system of claim 15, wherein the control unit is configured to control an operation of at least one device selected from the group consisting of (i) a digital processing unit of at least one transmitter of the plurality of transmitters, (ii) a digital-to-analog converter of at least one transmitter of the plurality of transmitters, (iii) an analog processing unit of at least one transmitter of the plurality of transmitters, and (iv) a transmit antenna of at least one transmitter of the plurality of transmitters, and wherein the control unit is configured to control an operation of at least one device selected from the group consisting of (i) a receive antenna of at least one receiver of the plurality of receivers, (ii) an analog processing unit of at least one receiver of the plurality of receivers, (iii) an analog-to-digital converter of at least one receiver of the plurality of receivers, (iv) a digital front end processing unit of at least one receiver of the plurality of receivers, and (v) a digital back end processing system of at least one receiver of the plurality of receivers.

18. The radar sensing system of claim 15, wherein the control unit is configured to control an operation of at least one receiver of the plurality of receivers to process range information from the received radio signals, and wherein the at least one receiver is configured to:

identify a set of objects with a highest received signal strength;

estimate a Doppler velocity for the objects using one of a median, a weighted arithmetic mean, and a weighted geometric mean of corresponding samples for different range bins associated with an object;

calculate one of (i) a first phase shift, from one complex correlator input sample to a next complex correlator input sample, that corresponds to the estimated Doppler velocity, and (ii) a second phase shift, from one com-

plex correlator output sample to a next complex correlator output sample, that corresponds to the estimated Doppler velocity; and
derotate an Nth complex sample pre or post correlator by a multiple of one of the first phase shift and the second phase shift, depending on which phase shift was estimated. 5

19. The radar sensing system of claim **15**, wherein the control unit is configured to control an operation of at least one receiver of the plurality of receivers to process range information from the received radio signals, and wherein the at least one receiver is configured to: 10

select an object for which a better Doppler estimation is desired;
store multiple time scans corresponding to a range of a desired object; and 15
perform Doppler processing on extended information from multiple scans to obtain more precise Doppler information.

20. The radar sensing system of claim **15**, wherein the control unit is configured to control an operation of each transmitter of the plurality of transmitters and each receiver of the plurality of receivers to correlate with a specified set of range bins to generate the range information data stored in memory, and wherein a difference between consecutive range bins increases as the range increases. 25

21. The radar sensing system of claim **15**, wherein the control unit is configured to control an operation of at least one of the plurality of transmitters and the plurality of receivers based upon external information received by the radar sensing system. 30

* * * * *

UNITED STATES PATENT AND TRADEMARK OFFICE
CERTIFICATE OF CORRECTION

PATENT NO. : 10,145,954 B2
APPLICATION NO. : 15/844994
DATED : December 4, 2018
INVENTOR(S) : Curtis Davis et al.

Page 1 of 2

It is certified that error appears in the above-identified patent and that said Letters Patent is hereby corrected as shown below:

In the Specification

Column 12

Line 12, "I/O" should be --I/Q--.

Column 14

Line 35, "I/O" should be --I/Q--.

In the Claims

Column 19

Line 8, Claim 1, delete "dynamically adaptable".

Column 19

Line 9, Claim 1, delete "dynamically adaptable".

Column 19

Line 66, Claim 5, "one" should be --a first--.

Column 20

Line 2, Claim 5, "one" should be --a second--.

Column 21

Line 17, Claim 12, "one" should be --a first--.


Column 21

Line 20, Claim 12, "one" should be --a second--.

Column 21

Line 54, Claim 15, delete "an".

Signed and Sealed this
Eleventh Day of June, 2019



Andrei Iancu
Director of the United States Patent and Trademark Office

CERTIFICATE OF CORRECTION (continued)
U.S. Pat. No. 10,145,954 B2

Column 22

Line 20, Claim 16, "requirement" should be --requirements--.

Column 22

Line 64, Claim 18, "one" should be --a first--.

Column 22

Line 67, Claim 18, "one" should be --a second--.




FIG. 5




FIG. 6




FIG. 8




FIG. 10




FIG. 11a




FIG. 11c




FIG. 11d

SOFTWARE DEFINED AUTOMOTIVE RADAR SYSTEMS

CROSS REFERENCE TO RELATED APPLICATIONS

The present application is a continuation application of U.S. patent application Ser. No. 15/496,313, filed Apr. 25, 2017, now U.S. Pat. No. 9,846,228, which claims the filing benefits of U.S. provisional applications, Ser. No. 62/327,003, filed Apr. 25, 2016, Ser. No. 62/327,004, filed Apr. 25, 2016, Ser. No. 62/327,005, filed Apr. 25, 2016, Ser. No. 62/327,006, filed Apr. 25, 2016, Ser. No. 62/327,015, filed Apr. 25, 2016, Ser. No. 62/327,016, filed Apr. 25, 2016, 62/327,017, filed Apr. 25, 2016, and Ser. No. 62/327,018, filed Apr. 25, 2016; and U.S. patent application Ser. No. 15/496,313 is a continuation-in-part of U.S. patent application, Ser. No. 15/481,648, filed Apr. 7, 2017, now U.S. Pat. No. 9,689,967, which claims the filing benefits of U.S. provisional applications, Ser. No. 62/319,613, filed Apr. 7, 2016, and Ser. No. 62/327,003, filed Apr. 25, 2016, which are all hereby incorporated by reference herein in their entireties.

FIELD OF THE INVENTION

The present invention is directed to radar systems, and in particular to radar systems for vehicles.

BACKGROUND OF THE INVENTION

The use of radar to determine range, velocity, and angle (elevation or azimuth) of objects in an environment is important in a number of applications including automotive radar and gesture detection. A radar typically transmits a radio frequency (RF) signal and listens for the reflection of the radio signal from objects in the environment. A radar system estimates the location and velocity of objects, also called targets, in the environment by comparing the received radio signal with the transmitted radio signal. It would be advantageous to have a radar system that can adapt various aspects of the radar transmitted signal and receiver processing to different environments and different objective functions.

SUMMARY OF THE INVENTION

The present invention provides methods and a radar system that can operate under a variety of environments, a variety of external information, and with a variety of objective functions to modify the transmission and reception processing at a given time to optimize the system with respect to a given objective function. The invention accomplishes better performance by adaptively changing the system including changing the transmitted signal characteristics such as the baseband signal, the bandwidth, the frequency, and the power and the set of transmitting antennas that are used. Better performance is also obtained by changing the receiver processing including the receiving antennas, interference mitigation techniques to be employed, length of time of the signal used to process a received signal to determine range.

A radar sensing system for a vehicle in accordance with an embodiment of the present invention includes a plurality of transmitters, a plurality of receivers, a memory, and a control unit. The plurality of transmitters is configured for installation and use on a vehicle and operable to or config-

ured to transmit modulated radio signals. The plurality of receivers are configured for installation and use on the vehicle and operable to or configured to receive radio signals that are transmitted radio signals reflected from an object in the environment. Each transmitter of the plurality of transmitters comprises a digital processing unit, a digital-to-analog converter, an analog processing unit, and a transmit antenna. Each receiver of the plurality of receivers comprises a receive antenna, an analog processing unit, an analog-to-digital converter, a digital front end processing unit, and a digital back end processing system. The control unit is operable to or configured to select an operating mode and to modify the plurality of transmitters and the plurality of receivers. Range information data produced by the digital front end processing unit is stored in the memory and then processed by the digital back end processor, as directed by the control unit. The range information data, which includes range information of objects in the environment, is stored in the memory for different receivers and for different scans. The processing of the range information data is controlled by the control unit.

A method for operating a dynamically adaptable, modulated continuous wave vehicular radar system in accordance with an embodiment of the present invention. The method includes providing a transmitter and a receiver, both configured for installation and use on a vehicle. The transmitter is operable to or configured to transmit a modulated radio signal. The receiver is operable to or configured to receive a radio signal that is a transmitted radio signal reflected from an object in the environment. The receiver comprises a dynamically adaptable digital front end processor and a dynamically adaptable digital back end processor. In response to environmental conditions and an operational status, an operating mode and a modification of an operational parameter of at least one of the transmitter and the receiver are selected, the selection depending on a need for one of a best range resolution and a best velocity resolution. Range information data is stored into memory that was produced by the digital front end processing unit. The digital back end processor is directed to process a selected portion of the range information data, based upon the selected operating mode.

These and other objects, advantages, purposes and features of the present invention will become apparent upon review of the following specification in conjunction with the drawings.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 is a plan view of an automobile equipped with a radar system in accordance with the present invention;

FIGS. 2A and 2B are block diagrams of single transmitter and receiver in a radar system;

FIG. 3 is a block diagram of multiple transmitters and multiple receivers in a radar system;

FIG. 4 is a block of a single receiver and single transmitter;

FIG. 5 is a graph illustrating an exemplary transmitted signal using an m-sequence of length 31 in accordance with the present invention;

FIGS. 6-9 are graphs illustrating exemplary matched filter outputs over time in accordance with the present invention;

FIG. 10 is a graph illustrating an exemplary imagery part of filter output vs a real part of filter output in accordance with the present invention; and

Radars must operate in various environments. For example, an automotive radar must operate in urban areas, suburban areas, rural areas, rain, snow, deserts, parking lots, garages, construction zones, to name a few. Depending on the installation location of the radar in an automobile, the transmitted signal might be reflected off of parts of the automobile. For example, reflections from a bumper in the automobile might create very strong self-interference. The set of environments an automobile is expected to operate in is extensive. Depending on the environment different types of signals might be used. A radar signal appropriate for one environment will not be the best signal to use in a different environment. The receiver processing used will also depend on the environment. The environment might be determined from the radar itself but also could be obtained by the radar from external sources (e.g., other vehicles, cellular networks, GPS).

In addition to operating in multiple environments, radar systems may have different performance objectives. Range resolution, maximum unambiguous range, Doppler resolution, angular resolution, and field of view are some of the objectives of a radar system. The smallest separation of two objects, such that they are recognized as two distinct objects by a radar, is known as the range resolution of the radar. The range resolution is inversely proportional to the bandwidth of the transmitted signal. A short-range radar (SRR) might provide a range resolution that is sub-meter (e.g., less than 5 cm) but only for distances from 0 to less than 30 meters. A long-range radar might have a much larger range resolution. Another performance measure is the maximum unambiguous range, D_u . This is the maximum distance of an object such that the distance can be correctly (unambiguously) determined from the received (reflected) signal. If the delay of the reflected signal can be confused with another (shorter) delay due to the period of the transmitted signal, then the distance to the object cannot be unambiguously determined. A long-range radar (LRR) might have a maximum unambiguous range out to several hundred meters whereas a SRR might have an unambiguous range out to several tens of meters.

Doppler resolution refers to the capability of a radar to discriminate the velocity of different targets. There is a maximum Doppler shift that a radar can determine without ambiguity. This is known as the maximum unambiguous velocity. A radar system using multiple antennas can determine the angle of a target relative to some reference in either the horizontal plane (azimuth) or the elevation angle (angle relative to the horizontal plane). A set of angles for which a radar can detect an object is called the field of view. Generally, with a fixed number of antennas, a large field of view would result in less angular resolution while a narrow field of view can provide better angular resolution. With certain antenna configurations, the elevation angle of an object can be determined.

The description herein includes a radar system in which there are N_T transmitters and N_R receivers $N_T \times N_R$ virtual radars, one for each transmitter-receiver pair. For example, a radar system with eight transmitters and eight receivers will have 64 pairs or 64 virtual radars (with 64 virtual receivers). When three transmitters (Tx1, Tx2, Tx3) generate signals that are being received by three receivers (Rx1, Rx2, Rx3), each of the receivers is receiving the transmission from each of the transmitters reflected by objects in the environment. Each of the receivers is receiving the sum of reflected signals due to all three of the transmissions at the same time. Each receiver can attempt to determine the range and Doppler of objects by correlating with delayed replicas

of the signal from one of the transmitters. The physical receivers may then be "divided" into three separate virtual receivers, each virtual receiver correlating with a replica of one of the transmitted signals. In a preferred radar system of the present invention, there are 1-4 transmitters and 4-8 receivers, or more preferably 4-8 transmitters and 8-16 receivers, and most preferably 16 or more transmitters and 16-64 or more receivers.

As mentioned earlier, there are various types of signals used in radar systems. A pulsed radar transmits a signal for a short duration of time then turns off the transmitter and listens for reflections. A continuous wave radar transmits a continuous signal. One type of continuous wave radar signal is known as frequency modulated continuous wave (FMCW) signal. The frequency of this signal is varied from some low frequency value to a high frequency value over some time interval and then repeats. Another type of continuous wave radar signal is known as phase modulated continuous wave (PMCW). The phase of the transmitted signal is varied in PMCW. Often the variation of the phase is according to a spreading code. The spreading code may be binary (e.g., +1 and -1) in which case the phase of the transmitted signal at any time takes on one of two possible values (e.g., 0 and π radians). Spreading codes with more than two levels can also be used. Often the code repeats after a certain duration in time duration, sometimes called the pulse repetition interval (PRI). Various types of spreading codes can be used. These include pseudorandom binary sequence (PRBS) codes also called m-sequences, almost perfect autocorrelation sequences (APAS), Golay codes, constant amplitude zero autocorrelation codes (CAZAC) also known as Frank-Zadoff-Chu (FZC) sequences, as well as many other codes that can be used. In a radar system with a single antenna, a single spreading code is used. The autocorrelation of this single code determines the capability of the radar to estimate the range (range resolution and maximum unambiguous range). Codes with good autocorrelation properties include Barker sequences, m-sequences, FZC sequences, and Golay codes. These codes have small sidelobes (the off-center autocorrelation). Codes that have ideal autocorrelation (e.g., Golay codes, CAZAC) can have range sidelobes in the presence of non-zero Doppler shift that will limit the detectability of far targets in the presence of near targets.

In a multiple-input, multiple-output (MIMO) system, there are multiple transmitters that operate simultaneously. Each transmitter uses a spreading code and thus multiple codes are needed, one for each transmitter. In this case (multiple transmitters), codes that have good autocorrelation, as well as good cross correlation properties are desirable. Generally, the better the autocorrelation of codes, the worse the cross correlation properties.

FIG. 5 shows a baseband signal which has a period of $L_C=31$. The chips in this example are from a maximal length sequence (m-sequence) of length $L_C=31$ generated by an exemplary shift register of length 5. Note that the signal repeats every L_C chips or $L_C T_C$ seconds. The pulse repetition rate is $R_{PR} = 1/(L_C T_C)$. The transmitted signal is generated from the baseband signal by modulating the baseband signal onto a carrier frequency to generate a radio frequency signal.

As illustrated in FIG. 4, the received signal is down-converted to a complex baseband signal via an RF front end analog signal processing 470. The analog signal processing involves amplification, mixing with a local oscillator signal, and filtering. The mixing is with two sinusoidal signals that are 90 degrees out of phase (e.g., cosine and sine or in-phase and quadrature-phase signals). After down conversion, the

with a given delay (e.g., corresponding to the delay with a given target) is calculated. This correlation calculation generates a complex number for a given delay and this repeats N times during a scan. The N complex numbers can be used to determine the Doppler frequency shift at the given delay. In the absence of Doppler frequency shift the complex correlation values will be constant. In the presence of a Doppler shift the complex correlation values will rotate. The rate of rotation will be related to the Doppler frequency. FIG. 9 illustrates the real and imaginary parts of the matched filter output when there is a Doppler shift. FIG. 10 illustrates the complex values at the peak correlation outputs. As can be seen, the matched filter output is rotating around a circle. The rate of rotation is a measure of the Doppler frequency. Knowing the Doppler frequency allows a calculation of the relative velocity of a target.

One way to estimate the Doppler frequency is to use a fast Fourier transform (FFT) on the complex samples. With this approach to estimating the frequency shift due to Doppler, with N points as the input to the FFT, there will also be N frequency points generated. The frequency resolution possible is over the range of frequencies from a negative frequency of $-R_{PR}/2$ to a positive frequency $+R_{PR}/2$ or a range of R_{PR} . Thus, the spacing between frequency points will be $f_R=R_{PR}/N$. This is the frequency resolution. This corresponds to a velocity resolution of:

$$V_r = c R_{PR} / (2f_c N)$$

If the complex correlation samples are produced at a rate of $R_{PR}=1/T_{PR}=1/L_C T_C$, then the frequency range that those points represent is limited to $-R_{PR}/2$ to $+R_{PR}/2$. Thus, the maximum unambiguous differential frequencies f_u that can be represented is given by $-R_{PR}/2 < f_u < +R_{PR}/2$. When this is converted to velocity, the result is that the maximum unambiguous velocity is limited to values in the interval shown below:

$$-cR_{PR}/(4f_c) < v_u < +cR_{PR}/(4f_c)$$

Increasing the repetition rate increases the maximum unambiguous velocities that can be determined. However, increasing the repetition rate decreases the maximum unambiguous range that can be determined. The product of the maximum unambiguous velocity and maximum unambiguous range is limited as

$$-c^2/(8f_c) < D_u V_u < c^2/(8f_c)$$

which is independent of the various parameters of the transmitted signal, except the carrier frequency.

The product of the velocity resolution and the range resolution is given as

$$D_r V_r = c^2 / (4F_C L_C N)$$

where L_C is the number of chips in a single period of the spreading code and N is the number of points in the FFT used to determine the velocity. For a fixed scan time ($L_C N T_C$) and fixed chip duration T_C , there is a tradeoff between the resolution possible for the range and the resolution possible for the velocity. By increasing N and decreasing L_C , the velocity resolution improves at the expense of range resolution. Similarly, decreasing N and increasing L_C will improve the range resolution at the expense of velocity resolution.

In some systems the signal has L_C chips per period but this sequence is repeated M times and the correlation values are accumulated to generate a signal complex sample for a given range. The sequence of such samples is then used for Doppler processing.

The above illustrates a tradeoff between the maximum unambiguous range and the maximum unambiguous velocity that only depends on the carrier frequency. An increased product of unambiguous velocity and range can only be obtained if the carrier frequency is decreased. In some circumstances, it might be desirable to obtain a larger unambiguous range at the expense of a smaller unambiguous velocity (or vice versa). Thus, a system that can adjust the repetition frequency of the signal would be able to adjust to different objectives. There is also a tradeoff between range resolution and velocity resolution for a given bandwidth and scan duration. In some situations, it would be advantageous to have better range resolution while in other cases it would be beneficial to have better velocity (or Doppler) resolution. Thus, it would be of benefit to be able to adjust the system parameters depending on the objective function of interest to obtain either the best range resolution or the best velocity resolution (with a given fixed time interval for the scan).

As an example, consider a radar system with a desired scan duration (time to produce a velocity estimate) of 0.1 ms (100 scans per second). Suppose the chip rate is fixed at 10^8 seconds and the carrier frequency is 79 GHz. A spreading code period of 100 chips would allow 1000 repetitions in the scan time. This corresponds to an unambiguous range of 150 m and an unambiguous velocity estimate range of (-950 m/s, +950 m/s). On the other hand, a spreading code period of 1,000 would allow only 100 repetitions of the code in the same time. The unambiguous range would increase to 1,500 m, while the unambiguous velocity would decrease to (-95 m/s, +95 m/s).

At the receiver it is necessary to store the complex outputs of the correlators for different possible ranges and for different receivers. A sequence of N complex samples needs to be stored for a particular range and a particular virtual receiver (a receiver matched to a particular spreading code of a transmitter) in order to determine an estimate of the velocity for an object at a particular range. For example, suppose that there are 512 range bins desired to locate potential targets and the number of repetitions of the code is 1024. This would require storing 512×1024 complex numbers with each complex number requiring 4 bytes of storage. This would require more than 2 million bytes of storage per virtual receiver. If there are 4 transmitting antennas and 16 receiving antennas then this would require about 134 Mbytes of storage, much more than is practical with current storage limits integrated onto a chip. On the other hand, storing this off chip would require a significant amount of time to transfer data. At a rate of 1600 Mbytes/second only about 12 transfers could happen per second. The number of virtual receivers determines the possible angle resolution. More receivers can provide more angular resolution at the expense of additional storage or at the expense of worse range or velocity resolution. Thus, the storage restrictions limit either the angular resolution, the range resolution, or the velocity resolution.

In automotive radar systems, there are various objects in the environment that reflect the transmitted signals of the radar. Some of the objects are stationary objects such as road signs, parked cars, light poles and such. There are numerous such objects that are stationary but since the automobile containing the radar is moving, these objects generate reflected signals with Doppler shift relative to the transmitted signal. On the other hand, there are objects such as other vehicles which are not stationary in the environment and have a different Doppler shift than stationary objects. Often, the stationary objects appear as a dense collection of radar returns for different ranges and different angles, whereas

a Doppler shift. By taking the fast Fourier transform of RDC1, with respect to the time dimension, the Doppler at a given range, and for a given virtual receiver, can be determined. This information is stored in radar data cube 2 (RDC2). The Doppler processing (1180) has as input of time samples and performs a Fourier transform processing (e.g., FFT, DFT or channelizer) to generate Doppler information stored in RDC2 (1182). The time samples can be windowed as needed or zero padded, depending on the radar system objective and/or external inputs. One type of windowing is a rectangular window which allows for accurately estimating the peak of strong signals at the expense of poorer sidelobe suppression. A Dolph-Chechyshev windowing supports greater side-lobe suppression to allow detection of weaker signals that would otherwise be hidden by the side-lobes of the stronger signals. The signal samples can also be padded to obtain better Doppler sampling granularity. The window used and the padding employed are fully controllable from the control processor. Radar data cube 2 (RDC2) stores complex samples in three dimensions: range, Doppler, and virtual receiver.

The next step in processing the data is using the RDC2 information to calculate the angle of arrival for a particular range and a particular Doppler shift. This is done in angle processor 1184. The resulting information is stored in RDC3 which has dimensions corresponding to range, Doppler, and angle (azimuth and/or elevation). The angle of arrival processing (1184) does a beam forming type of algorithm on the RDC2 data as a function of the virtual receiver. The angle processor does beam forming using a steering vector to weight the different receiver outputs and combine the weighted outputs. The beam forming used will depend on the particular set of antennas employed, as configured by the control processor. Aspects of such beam forming are also discussed in U.S. patent application Ser. No. 15/496,038, filed concurrently with the present patent application, and titled SOFTWARE DEFINED AUTOMOTIVE RADAR (“the ’038 patent application”), which is hereby incorporated by reference herein in its entirety.

Since the antennas are switchable, the angle of arrival calculation is dependent on the selection of antennas. Storage of information in RDC2 and RDC3 can be implemented with a first in, first out (FIFO) buffer where all the information associated with a particular scan (e.g., range, Doppler and virtual receiver) are not necessarily stored simultaneously but are being written into the FIFO while other information is being read out.

The analog processing of the received signal from the antenna to the ADC is called the analog front end. The processing of digital signals from the ADC to RDC1 is called the digital front end. The control of these operations is done by a processor as described in the ’038 patent application, incorporated above.

The same processor controls the further processing of signals from RDC1 to RDC3 and then post RDC3 processing. This processing of digital signals from the RDC1 to generate Doppler information and angle information, along with the range information already determined, which is stored in radar data cube 3 (RDC3), is called the digital back end.

As mentioned above, the signals to be used for transmitting, and the receiver processing to be employed, depend on a number of different factors including the environment (e.g., an urban area, suburban area, parking lot, garage, construction zone etc.). Different, changing objectives for the radar system might be desired (e.g., small range resolution, small velocity resolution, small angular resolution,

etc.). Different types of interference might be present in the radar system (e.g., FMCW radars, PMCW radars, etc.). Therefore, it is desirable to be able to dynamically adapt the radar to different environments, different performance objectives, different external inputs, and different types of interference. Embodiments of the present invention provide for a software controllable adaptable radar system.

Radar Data Compression

In a radar system, Doppler processing typically comprises performing a fast Fourier transform (FFT) using a sufficiently long time series of complex data at the input to the FFT. This Doppler processing is performed independently on multiple time series, captured simultaneously by multiple virtual receivers for multiple range bins. However, the entire time series must be available before FFT processing can begin. This requires partial time series to be stored in memory as the points of the time series are captured, which can result in a large amount of memory being used. To enable longer scans, or scans with more virtual receivers, or more range bins, and using a limited amount of memory, it is desirable to first compress the time series as they are captured, then store the compressed representations in memory, and once they are fully captured, decompress them prior to performing Doppler processing on them. The compression should be lossless to avoid introducing compression artifacts into the data. There are various lossless compression algorithms that can be employed. For example, MPEG4-audio lossless coding (MPEG4-ALS) is one compression standard that has various parameters that can change the amount of compression and change the complexity of the algorithm. In MPEG4-ALS, data is the input to a predictor. The difference between the predicted value and the actual value is compressed using a form of entropy coding. Data may be optionally converted from complex in-phase and quadrature (I/Q) format to phase angle and magnitude format prior to the prediction step. After prediction, residual values (the difference between the predicted value and the actual value) are compressed using an arithmetic or entropy encoding algorithm. Within a given range bin, predictors predict samples of data based on the value of samples from adjacent virtual receivers (to either side of the sample being predicted), and from previous time samples for the same virtual receiver. Inter-range bin prediction may also be used. The compression of data that is stored in RDC1 (for later Doppler processing) is controlled by software and can be adapted to achieve certain objectives, such as processing time and memory requirements.

Compensating for Doppler Shift:

Doppler shift has an adverse effect on a radar system’s ability to correlate a received signal with various delayed or shifted versions of the transmitted signal to determine range. Because the phase of the received signal rotates due to Doppler shift, the magnitude of the peak corresponding to the delay of a target (so called zero-shift) decreases with increasing Doppler. Also, the average magnitude of the non-zero-shift “sidelobes” increases with increasing Doppler. The effect is that the SNR for the target in question is reduced and the SNR for all targets in all other range bins (non-zero shifts) decreases because the noise or interference from one target is now spread over different range bins. Naturally, largest target(s) cause the largest sidelobes. The present invention incorporates a method and device for compensating for Doppler shift, comprising:

- a. Identifying a set of the largest (highest received signal) targets;
- b. Estimating the Doppler velocity for the largest targets using a median, a weighted arithmetic mean, or a

15

- weighted geometric mean of the Doppler for several adjacent range bins that correspond to the target;
- c1. Calculating the phase shift, ϕ_1 , from one complex correlator input sample to the next complex correlator input sample, corresponding to the estimated Doppler velocity; and/or
 - c2. Calculating the phase shift, ϕ_2 , from one complex correlator output sample to the next complex correlator output sample, corresponding to the estimated Doppler velocity; and
 - d. Derotating the Nth complex (pre or post correlator) sample by $N^* \phi_1$ or $N^* \phi_2$.

A processor controls the identification of the set of largest targets. In the case of a single large target, no additional memory is required. In the case of two or more large targets, multiple (full or partial) RDC1 cubes are required. The processor also controls the estimation of the Doppler of the large target(s).

On Demand Multi-Scan Micro-Doppler:

In a radar system, achieving high Doppler resolution requires long scans. Practical limitations on the length of a scan, such as memory usage, and the desire to obtain frequent updates from the radar, limit the maximum achievable Doppler resolution in a single scan. Typical scans may be able to achieve Doppler resolutions of up to 0.1 meters/second. A system and methods for achieving high resolution Doppler measurements for selected targets by combining information from multiple scans is described in detail in U.S. Pat. No. 9,599,702.

While memory considerations prevent saving the entire raw radar data cube ("RDC1") from multiple scans, it is possible to identify and save only a subset of the data cube (e.g., a small subset of the range bins), the subset comprising a time series of complex valued samples of the signal from each virtual receiver for the range bin, or bins, of interest.

Once the data for a particular range bin (or bins) has been saved to memory for multiple consecutive scans, using the same scan parameters, micro-Doppler post processing can be performed, comprising the steps of concatenating or joining or linking each time series, optionally inserting zeros in the time series to compensate for any delays between scans, performing a fast Fourier transform (FFT) on each time series to convert them from the time domain to the Doppler frequency domain (or alternatively using a channelizer), followed by any angle-of-arrival processing (e.g., beamforming or angle super-resolution) that may be desired. The decision about when to perform such multi-scan processing and for which range bins to process is controlled a processor.

Fully Pipelined Architecture:

The present invention provides a fully reconfigurable, pipelined radar architecture, which allows the user to perform different radar scans for different use case scenarios while keeping the memory requirements fairly small. Aspects of such pipelined radar architecture are described in the '038 patent application, incorporated above. The architecture comprises:

1. A programmable PRN generator for non-periodic (PRBS based codes) and periodic codes (with support for Hadamard Matrix). The PRN generator supports switching of periodic codes for each FFT point as well as constructing PRBS sequences based on fully configurable HW generated PRBS sequences.
2. Fascia reflection self-Interference mitigation. Self-interference mitigation is discussed in U.S. patent application Ser. No. 15/496,314, filed concurrently with the present application and titled VEHICULAR RADAR SYSTEM

16

WITH SELF-INTERFERENCE CANCELLATION, now U.S. Pat. No. 9,791,551, which is hereby incorporated by reference herein in its entirety.

3. FIR decimation (Reduce frequency from 2 GHz to 75 MHz) /FIR range walking /FMCW canceler.
4. An FFT based correlator for range bins.
5. A Correction engine for successive cancelation as well as amplitude and phase correction.
6. Compression/de-compression of a radar data cube (time samples).
7. FFT channelizers or Doppler processing.
8. Angle of arrival computation (delay and sum /FFT)
9. Decimation to store only relevant information out of the radar data cube.

Only items 4 and 5 require a full radar data cube (RDC1). The steps afterwards require a much smaller temporary storage since the computations are done more or less in flight. The processing of the radar data cube is in general done faster compared to the accumulation of the new radar data cube to ensure minimal memory overhead. The control processor controls these operations.

Ghost Interference Removal:

In a PMCW radar, mitigation of the adverse effects of interference from other PMCW radars is difficult because, without knowledge of the exact code and carrier frequency used by the interfering radar, there is no straightforward way to suppress the interference. The spectrum spreading caused by the interfering radar's use of pseudo-random code sequences results in an elevated noise floor, which in turn reduces a radar's ability detect weak targets.

The present invention proposes a method and device to isolate and suppress the interference from another PMCW radar using periodic spreading codes, comprising the steps of: using a first periodic code with the same period as the interfering PMCW radar (but not necessarily the same code, or the same carrier frequency), capturing a first N time samples (aka: FFT points), then repeating with a second periodic code with the same period as first periodic code, and capturing a second N time samples, optionally repeating this process one or more additional times for a total of K times, and then performing Doppler processing on each of the K sets of N time samples to compute K frequency spectrums. The control processor compares the frequency spectrums and identifies the peaks (the "inconsistent signals") whose magnitude varies across the K frequency spectrums and the peaks (the "true signals") whose magnitude remains constant (or nearly so) across the K frequency spectrums. The control processor modifies or instructs the hardware to modify all captured time samples to remove frequencies that correspond to the inconsistent signals. Finally, a single FFT is performed over all K*N modified samples. This technique has been shown to lower the noise floor by 20 dB or more. Methods for mitigating interference from other PMCW radars is discussed in U.S. patent application, Ser. No. 15/416,219, filed Jan. 26, 2017, now U.S. Pat. No. 9,772,397, which is hereby incorporated by reference herein in its entirety.

The control processor identifies the existence of one or more interfering radars. The control processor also controls the type of spreading codes being used (the period, the type, etc.). Lastly, the control processor also controls the choice of K and N used for interference estimation. Memory Reduction by Beamforming and Decimation/Sparsification:

The present invention provides a method and device for reducing the amount of post Doppler processing data, in a

The invention claimed is:

1. A method for operating a dynamically adaptable vehicular radar system, the method comprising:
 - providing a transmitter configured for installation and use on a vehicle;
 - providing a receiver configured for installation and use on the vehicle;
 - wherein the receiver comprises a dynamically adaptable digital front end processor and a dynamically adaptable digital back end processor;
 - providing a memory;
 - transmitting radio signals using the transmitter;
 - receiving radio signals using the receiver, wherein the received radio signals include transmitted radio signals transmitted by the transmitter and reflected from objects in an environment;
 - controlling an operation of at least one of the transmitter and the receiver to provide at least one of a selected range resolution, a selected velocity resolution, and a selected angle of arrival resolution; wherein controlling the operation of at least one of the transmitter and the receiver is dynamically and adaptively variable, as defined by a selected functional requirement and a current environmental condition, and wherein the functional requirement comprises at least one of a selected processing time and a memory requirement;
 - storing data into the memory that was produced by the digital front end processing unit from the received radio signals; and
 - directing the digital back end processor to process the stored data based upon the controlled operation of the at least one of the transmitter and the receiver.
2. The method of claim 1, wherein, for a given radio signal bandwidth and receiver scan duration, selection of a velocity resolution comprising an increased velocity resolution results in selection of a range resolution comprising a decreased range resolution.
3. The method of claim 1, wherein, for a given radio signal bandwidth and receiver scan duration, selection of a range resolution comprising an increased range resolution results in selection of a velocity resolution comprising a decreased velocity resolution.
4. The method of claim 1, wherein controlling an operation of the transmitter comprises controlling an operation of at least one device selected from the group consisting of (i) a digital processing unit of the transmitter, (ii) a digital-to-analog converter of the transmitter, (iii) an analog processing unit of the transmitter, and (iv) a transmit antenna of the transmitter, and wherein controlling an operation of the receiver comprises controlling an operation of at least one device selected from the group consisting of (i) a receive antenna of the receiver, (ii) an analog processing unit of the receiver, (iii) an analog-to-digital converter of the receiver, (iv) a digital front end processing unit of the receiver, and (v) a digital back end processing system of the receiver.
5. The method of claim 1, wherein controlling an operation of the receiver comprises controlling the receiver to process range information from the received radio signals, and wherein the receiver is configured to:
 - identify a set of objects with a highest received signal strength;
 - estimate a Doppler velocity for the objects using one of a median, a weighted arithmetic mean, and a weighted geometric mean of corresponding samples for different range bins associated with an object;
 - calculate one of (i) a first phase shift, from one complex correlator input sample to a next complex correlator

- input sample, that corresponds to the estimated Doppler velocity, and (ii) a second phase shift, from one complex correlator output sample to a next complex correlator output sample, that corresponds to the estimated Doppler velocity; and
 - derotate an Nth complex sample pre or post correlator by a multiple of one of the first phase shift and the second phase shift, depending on which phase shift was estimated.
6. The method of claim 1, wherein controlling an operation of the receiver comprises controlling the receiver to process range information from the received radio signals, and wherein the receiver is configured to:
 - select an object for which a better Doppler estimation is desired;
 - store multiple time scans corresponding to a range of a desired object; and
 - perform Doppler processing on extended information from multiple scans to obtain more precise Doppler information.
 7. The method of claim 1, wherein controlling an operation of at least one of the transmitter and the receiver is based upon external information received by the radar sensing system.
 8. A radar sensing system for a vehicle, the radar sensing system comprising:
 - a transmitter configured for installation and use on a vehicle, and configured to transmit radio signals;
 - a receiver configured for installation and use on the vehicle, and configured to receive radio signals, wherein the received radio signals include transmitted radio signals transmitted by the transmitter and reflected from objects in an environment;
 - a memory;
 - a control unit configured to control an operation of at least one of the transmitter and the receiver to provide at least one of a selected range resolution, a selected velocity resolution, and a selected angle of arrival resolution, wherein the control unit is further configured to dynamically and adaptively vary the operation of at least one of the transmitter and the receiver, as defined by a selected functional requirement and a current environmental condition, and wherein the functional requirement comprises at least one of a selected processing time and a memory requirement;
 - wherein data produced by the receiver from the received radio signals is stored in the memory; and
 - wherein the control unit controls the processing of the stored data based upon the controlled operation of the at least one of the transmitter and the receiver.
 9. The radar sensing system of claim 8, wherein, for a given radio signal bandwidth and receiver scan duration, selection of a velocity resolution comprising an increased velocity resolution results in selection of a range resolution comprising a decreased range resolution.
 10. The radar sensing system of claim 8, wherein, for a given radio signal bandwidth and receiver scan duration, selection of a range resolution comprising an increased range resolution results in selection of a velocity resolution comprising a decreased velocity resolution.
 11. The radar sensing system of claim 8, wherein the control unit is configured to control an operation of at least one device selected from the group consisting of (i) a digital processing unit of the transmitter, (ii) a digital-to-analog converter of the transmitter, (iii) an analog processing unit of the transmitter, and (iv) a transmit antenna of the transmitter, and wherein the control unit is configured to control an