



US008130139B2

(12) **United States Patent**  
**Taylor**

(10) **Patent No.:** **US 8,130,139 B2**  
(45) **Date of Patent:** **Mar. 6, 2012**

(54) **RADAR-BASED METHOD FOR MEASURING  
A LEVEL OF MATERIAL IN A CONTAINER**

(75) Inventor: **Andrew James Taylor**, Cumbria (GB)

(73) Assignee: **Siemens Aktiengesellschaft**, Munich  
(DE)

(\*) Notice: Subject to any disclaimer, the term of this  
patent is extended or adjusted under 35  
U.S.C. 154(b) by 393 days.

(21) Appl. No.: **12/437,010**

(22) Filed: **May 7, 2009**

(65) **Prior Publication Data**

US 2009/0278730 A1 Nov. 12, 2009

(30) **Foreign Application Priority Data**

May 9, 2008 (EP) ..... 08008780

(51) **Int. Cl.**  
**G01S 13/08** (2006.01)

(52) **U.S. Cl.** ..... **342/124**

(58) **Field of Classification Search** ..... **342/124**  
See application file for complete search history.

(56) **References Cited**

**U.S. PATENT DOCUMENTS**

5,504,490 A 4/1996 Brendle et al.  
5,614,911 A \* 3/1997 Otto et al. .... 342/124  
5,734,346 A \* 3/1998 Richardson et al. .... 342/124

5,948,979 A 9/1999 Fitsch et al.  
6,626,038 B1 9/2003 Carsella et al.  
7,518,548 B2 \* 4/2009 Edvardsson ..... 342/124  
7,999,725 B2 \* 8/2011 Feisst et al. .... 342/124  
8,040,274 B2 \* 10/2011 Wendler et al. .... 342/124  
8,044,843 B2 \* 10/2011 Baath ..... 342/124  
2004/0201516 A1 \* 10/2004 Lyon ..... 342/124  
2006/0132351 A1 \* 6/2006 Le Sesne ..... 342/124  
2007/0139256 A1 \* 6/2007 Edvardsson ..... 342/124  
2008/0034863 A1 \* 2/2008 Bartoli et al. .... 73/290 R  
2008/0143583 A1 \* 6/2008 Welle et al. .... 342/124  
2009/0278730 A1 \* 11/2009 Taylor ..... 342/124

**FOREIGN PATENT DOCUMENTS**

EP 2116819 A1 \* 11/2009  
WO WO 2008080840 A 7/2008

\* cited by examiner

*Primary Examiner* — John Sotomayor

(57) **ABSTRACT**

Described is a radar-based method for measuring a level of material in a container. Microwaves are emitted to a surface of the material by a radar level gauge, echo waves reflected from the surface are received and the received echo waves are converted into an echo function which is stored and evaluated to establish a useful echo and to determine a position of the echo. The echo function is generated and stored with a first higher resolution for a selected first portion of the entire level measurement range of the radar level gauge. Further, the echo function is generated and stored with a second lower resolution or no echo function is generated and stored for the remaining second portion of the entire level measurement range.

**11 Claims, 4 Drawing Sheets**




FIG 1




FIG 2




FIG 3




FIG 4





FIG 5



1

## RADAR-BASED METHOD FOR MEASURING A LEVEL OF MATERIAL IN A CONTAINER

### CROSS REFERENCE TO RELATED APPLICATIONS

This application claims priority of European Patent Application No. 08008780.2 EP filed May 9, 2008, which is incorporated by reference herein in its entirety.

### FIELD OF INVENTION

The invention relates to a radar-based method for measuring a level of material in a container.

### BACKGROUND OF INVENTION

For radar-based level measurement all known methods may be employed which permit distances to be measured by means of reflected microwaves, the best-known examples of which are pulsed radar and frequency modulated continuous wave radar (FMCW radar). In pulsed radar short microwave transmission pulses are emitted periodically which are reflected by the object being measured and re-received as an echo signal after a transit time depending on the distance involved. The received signal amplitude versus time function constitutes an echo function or echo profile. Every value of this echo function corresponds to the amplitude of an echo due to reflection at a certain distance from the antenna. In FMCW radar a continuous microwave is emitted which is periodically linearly frequency-modulated, for example, according to a saw-tooth function. The frequency of each received echo signal thus exhibits with respect to the instantaneous frequency which the transmission signal has at the time of reception, a difference in frequency which depends on the transit time of the echo signal. The difference between the frequency of the transmission signal and that of the reception signal which may be obtained by mixing both signals and evaluating the Fourier spectrum of the mixed signal, thus corresponds to the distance of the reflecting surface of the object away from the antenna, and the level of the frequency characteristic corresponds to the magnitude of the echo amplitude. This Fourier spectrum, therefore, constitutes the echo function in this case. In prior art the entirety of the echo function obtained in the course of a measurement cycle is stored and then the stored echo function is evaluated according to a given program by a computer to establish the useful echo and to determine the transit time of the useful echo. Storing the echo function in this case is preferably done in digitized form by the echo function being periodically sampled, each sampled value being converted by an analog-to-digital converter into a digital code group and the digital code groups being written into a RAM of the computer.

### SUMMARY OF INVENTION

Current radar level gauges waste time and power by always measuring over the entire measuring range and with the same resolution or accuracy.

According to the invention this problem is solved by a radar-based method as claimed in the independent claim.

Preferred embodiments of the invention are defined in the dependent claims.

The invention thus comprises a radar-based method for measuring a level of material in a container, comprising:

emitting microwaves to a surface of the material by means of a radar level gauge;

2

receiving echo waves reflected from the surface of the material using said radar level gauge;

converting the received echo waves into an echo function over time and storing the echo function;

evaluating the stored echo function to establish a useful echo and to determine the position of the useful echo, wherein the echo function is generated and stored with a first higher resolution for a selected first portion of the entire level measurement range of the radar level gauge and

wherein the echo function is generated and stored with a second lower resolution or no echo function is generated and stored for the remaining second portion of the entire level measurement range.

The range and resolution of the radar level gauge are variable and are focused on the selected first portion of the entire level measurement range where the useful echo may be expected or has been last determined. Once the useful echo has been detected, the first portion of the level measurement range is preferably centered around it. If the remaining second portion of the entire level measurement range of the radar level gauge is of no measurement interest, the generation, storing and evaluation of the echo function is limited solely to the first portion thus saving storing capacity and processing power and providing faster measurement. Otherwise, the echo function is generated and stored with a second lower resolution for the remaining second portion of the entire level measurement range. With the storage capacity being unchanged, the first higher resolution may be increased to the extent that the second lower resolution is decreased.

If there are two independent echoes of interest, the first useful echo is preferably established in one of two consecutive measurement cycles, whereas the other echo is established in the other measurement cycle by generating, storing and evaluating another echo function with said first or another higher resolution for a selected third portion of the entire level measurement range of the radar level gauge and wherein the other echo function is generated and stored with said second or another lower resolution or no echo function at all is generated and stored for the remaining fourth portion of the entire level measurement range. Here too, the third portion of the level measurement range is preferably centered around the last determined position of the other useful echo.

### BRIEF DESCRIPTION OF THE DRAWINGS

The invention will be now described in more detail with reference to preferred embodiments shown by way of non-limiting example in the attached drawings, wherein:

FIG. 1 is a schematic of a pulse radar level gauge,

FIG. 2 shows an echo function recorded in a conventional manner over the entire level measurement range of the radar level gauge,

FIG. 3 shows an echo function recorded according to a first embodiment of the invention,

FIG. 4 is a flow chart illustrating an algorithm used in the first embodiment of the invention, and

FIG. 5 shows an echo function recorded according to a second embodiment of the invention.

### DETAILED DESCRIPTION OF INVENTION

Referring to FIG. 1, which is a simplified schematic diagram, a pulse radar level gauge comprises a microwave transducer 1 which is installed in a tank 2 containing a liquid or other type of material 3, with a level determined by the top surface 4 of the material 3. The top surface 4 of the material 3

3

provides a reflective surface which reflects microwave pulses **5** generated from the transducer **1**. The transducer **1** is coupled to a microprocessor **6** through a transmitter **7**. The microprocessor **6** operates under a control program stored in read-only memory (ROM) **8**, utilizing parameters stored in non-volatile random access memory (NVRAM) **9**, and provided with a working memory in the form of random access memory (RAM) **10**.

The microprocessor **6** controls the transmitter **7** to excite the transducer **1** to emit the microwaves pulses **5** at predetermined points in time and with predetermined frequency and amplitude. The reflected or echo pulses **11** are received by the transducer **1** and converted to an electric signal which is then fed to a receiver **12**. The receiver **12** comprises an amplifier **13** and an envelope detector **14**. The output from the envelope detector **14** is then sampled and digitized by an analog-to-digital converter **15**, from where the digital echo profile is stored in the RAM **10** for further processing by the microprocessor **6**. Alternatively, the raw signal from the transducer **1** may be sampled and digitized before being envelope-detected. The microprocessor **6** executes an algorithm to identify the true echo **11** from the surface **4** of the material **3** and calculate the range of the reflective surface **4**, i.e. the time it takes for the echoes **11** to travel from the reflective surface **4** to the transducer **1**. From this calculation, the distance to the surface **4** of the material **3** and thereby the level of the material **3** is determined. An interface **16**, controlled by the microprocessor **6**, provides for the export of level-related data and the import of operating parameters. Data may be exported in the form of a display, telemetry (e.g. bus) signals, and/or alarm signals.

FIG. **2** shows a typical echo function **17** recorded in a conventional manner over the entire level measurement range of the radar level gauge. Many existing algorithms to identify a wanted echo in an echo function are well-known and well-documented and need not be described in more detail here. In the shown example, the true echo **18** from the top surface **4** of the material **3** is found at a distance of 9.00 m. As is apparent from FIG. **2**, recording and evaluating of the echo function **17** in the range between 0 m and approx. 8 m wastes measurement time and power.

FIG. **3** shows the echo function **19** recorded according to a first embodiment of the invention. The range and resolution of the radar level gauge are variable and are focused on a selected first portion or window **20** of the entire level measurement range. The window **20** is positioned where the useful echo **18** may be expected or has been last determined. Once the useful echo **18** has been detected, the window **20** of the level measurement range is centered around it. For the remaining second portion of the entire level measurement range, here the range from 0 m to 8 m and beyond 10 m, no echo function is generated. This will consume less power by only activating the receiver **12** for a short time and will provide faster measurements. At the same time, the resolution can be increased without requiring additional storage capacity since it is focused on only a portion **20** of the entire level measurement range.

Alternatively, e.g. for surveillance reasons, the echo function may be generated and stored for said remaining second portion with a lower resolution than that for the window **20**.

Referring to FIG. **4**, there will now be described an example of an algorithm executed by the microprocessor **6** to control the radar level gauge. The steps of the algorithm are:

1. The initial measuring range is set to the entire level measurement range of the radar level gauge with start point  $A = \text{Min} = 0 \text{ m}$  and stop point  $B = \text{Max} = 20 \text{ m}$ . The measurement resolution  $R$  is set to an initial value  $R = \text{normal value}$ .

4

2. A measurement is taken, the echo function **17** is recorded and evaluated over the entire level measurement range and the wanted echo **18** is identified at a distance (level)  $L$ .

3. The start point and stop point are set to  $A = L - (W/2)$  and  $B = L + (W/2)$ , where  $W = 2 \text{ m}$  is a predetermined width of the window **20**.

4. If required, the value of the measurement resolution  $R$  is increased.

5. A new measurement is taken and the echo function **19** is recorded and evaluated over the window **20**.

6. If the wanted echo **18** is identified within the window **20** at a distance  $L_{\text{new}}$ , the distance (level) is set to  $L = L + L_{\text{new}}$  and the algorithm is continued at step 3.

7. If the wanted echo **18** cannot be identified within the window **20**, the algorithm is continued at step 1.

FIG. **5** illustrates another example of the invention, where two different targets in the tank **2** are tracked. The wanted echo **18** from the first target (e.g. the top surface **4** of the material **3**) is identified in a first of two consecutive measurement cycles, as already described with reference to FIGS. **3** and **4**. In the same way, the other echo **21** from the second target (e.g. a stirrer) is established in the second measurement cycle by generating, storing and evaluating another echo function **22** for another selected portion (window) **23** of the entire level measurement range of the radar level gauge. It is also possible to record both echo functions **19** and **22** within the windows **20** and **23** in a single measurement cycle.

Although described above with particular reference to a pulse radar level gauge, the present invention may equally be used in other radar level gauges such as FMCW radar.

The invention claimed is:

1. A radar-based method for measuring a level of material in a container, comprising:

- emitting microwaves to a surface of the material by a radar level gauge;

- receiving echo waves reflected from the surface of the material using the radar level gauge;

- converting the received echo waves into an echo function over time;

- storing the echo function; and

- establishing a useful echo and determining a position of the useful echo by evaluating the stored echo function;

- wherein the echo function is converted and stored with a first higher resolution for a selected first portion of the entire level measurement range of the radar level gauge, and

- wherein the echo function is converted and stored with a second lower resolution or no echo function is converted and stored for the remaining second portion of the entire level measurement range.

2. The method according to claim 1, wherein the first portion of the entire level measurement range is centered around the last determined position of the useful echo.

3. The method according to claim 2, wherein the useful echo is established in one of two consecutive measurement cycles.

4. The method according to claim 3, further comprising:

- establishing another useful echo in the other measurement cycle of the two consecutive measurement cycles by converting, storing and evaluating another echo function with the first or another higher resolution for a selected third portion of the entire level measurement range of the radar level gauge and wherein the other echo function is converted and stored with the second or another lower resolution or no echo function is converted and stored for a remaining fourth portion of the entire level measurement range.

5

5. The method according to claim 4, wherein the third portion of the level measurement range is centered around the last determined position of the other useful echo.

6. The method according to claim 1, wherein the useful echo is established in one of two consecutive measurement cycles.

7. The method according to claim 6, further comprising: establishing another useful echo in the other measurement cycle of the two consecutive measurement cycles by converting, storing and evaluating another echo function with the first or another higher resolution for a selected third portion of the entire level measurement range of the radar level gauge and wherein the other echo function is converted and stored with the second or another lower resolution or no echo function is converted and stored for a remaining fourth portion of the entire level measurement range.

8. The method according to claim 7, wherein the third portion of the level measurement range is centered around the last determined position of the other useful echo.

9. A pulse radar level gauge, comprising:

a microwave transducer configured to generate microwave pulses, the microwave transducer being arranged in a tank containing a material and a top surface of the material providing a reflective surface to reflect the microwave pulses;

6

a transmitter;

a microprocessor, the microwave transducer being coupled to the microprocessor via the transmitter, and the microprocessor controlling the transmitter to excite the microwave transducer to emit the microwave pulses;

a receiver configured to receive an electric signal based upon reflected microwave pulses or echo pulses, the receiver having an amplifier and an envelope detector; and

a converter configured to generate a digital echo profile, wherein the microprocessor executes an algorithm to identify a true echo from the top surface of the material and to calculate a range of the reflective surface.

10. The pulse radar level gauge according to claim 9, wherein the microprocessor operates under a control program stored in a read-only memory (ROM), utilizing parameters stored in non-volatile random access memory (NVRAM) and provided with a working memory being a random access memory (RAM).

11. The pulse radar level gauge according to claim 9, further comprising:

an interface controlled by the microprocessor for an export of data and an import of operating parameters.

\* \* \* \* \*